

HPE Aruba Networking CX 6300 Switch Series



What's new

- The HPE Aruba Networking CX 6300 Switch Series is a family of stackable Layer 3 switches with BGP, EVPN, VXLAN, VRF, OSPF routing, robust quality of service (QoS), MACsec 256, PTP, AVB and LRM [1]
- Three stackable Layer 2-only CX 6300L switches with HPE Smart Rate multi-gigabit and MACsec 256 encryption are available for high-performance access deployments
- Powerful 7th Gen ASIC architecture provides the CX 6300 series with 880

Overview

The HPE Aruba Networking CX 6300 Switch Series is a modern, flexible, and intelligent family of stackable switches ideal for access, aggregation, and data center top-of-rack (ToR). It features a cloud-native design and fully programmable operating system (OS). The CX 6300 delivers advanced monitoring and troubleshooting with capabilities such as a real-time network analytics engine, HPE Aruba Networking Switch Multi-Edit Software and flexible deployment options to implement and validate network configurations.

A powerful Gen7 ASIC architecture delivers fast, non-blocking performance for AI, Wi-Fi 7, and Internet of Things (IoT) requirements. HPE Aruba Networking Virtual Stacking Framework (VSF) allows for stacking of up to 10 switches, providing scale and simplified management. This flexible series has built-in high-speed uplinks and supports high-density IEEE 802.3bt high-power PoE with HPE Smart Rate multi-gigabit Ethernet.

to 1760 Gbps system switching capacity, 660 to 1310 Mpps of system throughput and up to 200 to 400 Gbps stacking bandwidth

- High availability with choice between 2 to 10-member Virtual Switching Framework (VSF) stacking for scale, or 2-member Virtual Switching Extension (VSX) cluster for active-active redundancy
- Options include 24 to 48 HPE Smart Rate multi-gigabit ports (1/2.5/5/10GbE) and 1GbE fiber, supporting up to 90W 802.3bt PoE, all with telemetry and automation via the CX Network Analytics Engine
- Manage through a single point of control with HPE Aruba Networking Central across wired, wireless, and WAN. Dynamic segmentation enables enhanced security and simple access for users and IoT

Features

AI-ready performance and power

The HPE Aruba Networking CX 6300 Switch Series is a wire-speed solution that uses a fully distributed architecture with Gen7 ASICs that deliver low latency, increased packet buffering, and intelligent power consumption for AI, Wi-Fi 7, and Internet of Things (IoT) requirements.

HPE Aruba Networking Virtual Switching Framework (VSF) allows you to quickly grow your network using high-performance front-plane stacking. Four built-in uplinks support speeds of up to 10, 25, 50, and 100GbE for a total of 200 to 400 Gbps of stacking throughput per switch.

HPE Aruba Networking Virtual Switching Extension (VSX) and an inter-switch link (ISL) provide a high-availability solution that maintains state synchronization and an independent control plane across a 2-member active-active switch design [2].

HPE Smart Rate multi-gigabit Ethernet delivers adaptive speed options for Wi-Fi, Internet of Things (IoT), and other clients, alongside Class 4 (30W), Class 6 (60W), and Class 8 (90W) PoE on each port (720W, 1440W, and 2880W maximum PoE budget options).

Additional features include a hibernation mode that enables CX 6300 and CX 6300L (Layer 2-only) switches to schedule downtime to conserve energy. Note: CX 6300L stackable switches are Layer 2-only, balancing scalability, high-capacity, and cost-effective connectivity.

Automation and analytics

The HPE Aruba Networking CX 6300 Switch Series delivers enhanced visibility with built-in analytics for real-time monitoring and a time series database (TSDB) that stores configuration and operational state data, making it available to quickly resolve network issues.

HPE Aruba Networking Central provides secure, AI-native full-stack network management and operations to optimize performance, accelerate troubleshooting, and unify wired networks with Wi-Fi, wide area networks, and more.

HPE Aruba Networking CX Network Analytics Engine (NAE) provides real-time insights and actions, analyzing events that can impact network health and even mitigating problems directly through quarantining to support network, application, system and security operations.

HPE Aruba Networking Switch Multi-Edit Software introduces automation that allows for rapid network-wide changes and helps ensure policy conformance post network updates. Intelligent capabilities include search, edit, validation (including conformance checking), deployment, and audit features.

Import switch information into HPE Aruba Networking Switch Multi-Edit Software for simplified configuration management and for continual conformance validation.

Full stack management and security

The HPE Aruba Networking CX 6300 Switch Series is supported on HPE Aruba Networking Central for a single point of control management that delivers enhanced network visibility and an expanded AI toolset, addressing the scale and demands of the most mission-critical environments.

Dynamic segmentation that automatically applies and enforces user, device, and application-aware policies on HPE Aruba Networking wired and wireless infrastructures.

Automated device profiling, role-based access control, and Layer 7 firewall features deliver enhanced visibility and performance for a better end-user experience and streamlined IT operations. Application recognition and control are available through CX Advanced Feature Pack [1].

Switch-to-switch tunnels enable scalable multi-tenancy support with Virtual Extensible Local-Area Networks (VXLAN) to VRF mapping, while allowing policy application through user roles [1].

Reduce manual IT operations tasks around initial deployment or ongoing configuration changes to accommodate adds, moves, and changes with colorless ports using local user roles and local MAC authentication (LMA).

Deploy in data center topologies

HPE offers customers highly differentiated pre-engineered IT infrastructure solutions that span a wide variety of HPE Compute, HPE Storage, HPE Networking solutions supporting virtualization, vSAN™, HCI, HPC, MCS, Microsoft®, SAP HANA®, VMware®, Nutanix application and IaaS service offerings.

The 10/25GbE and 40/100GbE CX switches can be deployed as part of an HPE integrated and mixed compute, storage and networking configurations and deployments.

These ready-to-deploy, integrated IT data center solutions help simplify and speed IT service delivery while reducing the time, risk, and expertise needed to deploy complex solutions.

Technical specifications	HPE Aruba Networking CX 6300 Switch Series
Power consumption	Up to 211W depending on model
Input voltage	Maximum 120V/208V–240V depending on PSU model
Ports	Up to 48 HPE Smart Rate ports (1G/2.5G/5G/10GbE)
Latency	Depending on model
Switching capacity	From to 880 Gbps to 1760 Gbps, depending on model and configuration
Stacking capabilities	Up to 10 members per stack. Note: CX 6300L switches only stack with other CX 6300L switches
Throughput	From to 660 Mpps to 1310 Mpps, depending on model and configuration
Memory and processor	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration
Power supply	2 field-replaceable, hot-swappable power supply slots
PoE capability	Maximum PoE power: Up to 370W, 720W, 1440W, 2640W, or 2880W, depending on model and installed power supplies
Management features	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software
Operating temperature	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate -1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].
Shipping weight	13.27 lbs, maximum, depending on model
Shipping dimensions	1.73 x 17.4 x 15.2 in, maximum, depending on model
Warranty	Limited lifetime warranty . See warranty details.

SKU comparison

	HPE ANW CX 6300L 48p Smart Rate 100M/1G/2.5G/5G Class6/8 2p SFP56 50G 2p SFP+ 1G/10G LRM Layer2 Sw (S3L77A)	HPE Aruba Networking CX 6300F 24-port 1GbE and 4-port SFP56 Switch (JL668A)	HPE Aruba Networking CX 6300F 24-port 1GbE Class 4 PoE and 4-port SFP56 Switch (JL666A)	HPE Aruba Networking CX 6300F 24p 10M/100M/1G 4p SFP56 50G TAA Switch (S0G98A)	HPE Aruba Networking CX 6300F 24p 10M/100M/1G Class4 PoE 4p SFP56 50G TAA Switch (S0G96A)
Differentiator	Layer 2 only L switch does not support Layer 3 features in the F and M models Class 4 PoE/PoE+	Non-PoE	Class 4 PoE/PoE+	Non-PoE TAA certified	Class 4 PoE/PoE+ TAA certified
Power consumption	With single JL086A PSU: Idle: 207W 100% Traffic Rate: 283W With single JL087A PSU: Idle: 208W 100% Traffic Rate: 282W With single JL670A PSU: Idle: 211W 100% Traffic Rate: 283W	Idle: 49W 100% Traffic Rate: 63W	Idle: 52W 100% Traffic Rate: 67W	Idle: 49W 100% Traffic Rate: 63W	Idle: 52W 100% Traffic Rate: 67W
Input voltage	JL670A PSU: 110V-120V/208V-240V JL086A PSU: 100V-240V JL087A PSU: 110V-240V	Fixed PSU: 100V-120V/200V-240V	Fixed PSU: 100V-120V/200V-240V	Fixed PSU: 100V120V/200V240V	Fixed PSU: 100V120V/200V240V

	HPE ANW CX 6300L 48p Smart Rate 100M/1G/2.5G/5G Class6/8 2p SFP56 50G 2p SFP+ 1G/10G LRM Layer2 Sw (S3L77A)	HPE Aruba Networking CX 6300F 24-port 1GbE and 4-port SFP56 Switch (JL668A)	HPE Aruba Networking CX 6300F 24-port 1GbE Class 4 PoE and 4-port SFP56 Switch (JL666A)	HPE Aruba Networking CX 6300F 24p 10M/100M/1G 4p SFP56 50G TAA Switch (S0G98A)	HPE Aruba Networking CX 6300F 24p 10M/100M/1G Class4 PoE 4p SFP56 50G TAA Switch (S0G96A)
Ports	48x 10/100/1000 BaseT PoE+ ports supporting up to 30W per port 4x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on S0E91A and S0X44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.	24 x 10/100/1000 BaseT ports 4 x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port	24 x 10/100/1000 BaseT ports supporting up to 30W per port 4 x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port	24x 10/100/1000 BaseT ports 4x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on S0E91A and S0X44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.	24x 10/100/1000 BaseT ports supporting up to 30W per port 4x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on S0E91A and S0X44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.
Latency	1 Gbps: 4.24 s 10 Gbps: 1.50 s 25 Gbps: 2.91 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s
Switching capacity	720 Gbps	448 Gbps	448 Gbps	448 Gbps	448 Gbps
Stacking capabilities	Up to 10 members per stack. Note: CX 6300L switches only stack with other CX 6300L switches				
Throughput	535 Mpps	334 Mpps	334 Mpps	334 Mpps	334 Mpps

	HPE ANW CX 6300L 48p Smart Rate 100M/1G/2.5G/5G Class6/8 2p SFP56 50G 2p SFP+ 1G/10G LRM Layer2 Sw (S3L77A)	HPE Aruba Networking CX 6300F 24-port 1GbE and 4-port SFP56 Switch (JL668A)	HPE Aruba Networking CX 6300F 24-port 1GbE Class 4 PoE and 4-port SFP56 Switch (JL666A)	HPE Aruba Networking CX 6300F 24p 10M/100M/1G 4p SFP56 50G TAA Switch (S0G98A)	HPE Aruba Networking CX 6300F 24p 10M/100M/1G Class4 PoE 4p SFP56 50G TAA Switch (S0G96A)
Memory and processor	Quad Core Arm® Cortex® A72 @ 1.8GHz, 8 GB DDR4, 32 GB eMMC 16 MB Shared Packet Buffer Memory	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration
Power supply	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A.	Internal (fixed) power supply (200W)	Internal (fixed) power supply (950W)	Internal (fixed) power supply (200W)	Internal (fixed) power supply (950W)
PoE capability	Maximum PoE power: 2880W		Maximum PoE power: 370W		Maximum PoE power: 370W
Management features	1 default VRF, 1 management VRF	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software
Operating temperature	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate -1 degree C for every 1,000 ft from 5,000 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time. No more than 96 consecutive hours and no more than 360 hours total (15 days) in 1 year.	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].
Warranty	Limited lifetime warranty. See warranty details.				

	HPE Aruba Networking CX 6300F 48-port 1GbE and 4-port SFP56 Switch (JL667A)	HPE Aruba Networking CX 6300F 48-port 1GbE Class 4 PoE and 4-port SFP56 Switch (JL665A)	HPE Aruba Networking CX 6300F 48p 10M/100M/1G 4p SFP56 50G TAA Switch (SOG97A)	HPE Aruba Networking CX 6300F 48p 10M/100M/1G Class4 PoE 4p SFP56 50G TAA Switch (SOG95A)	HPE Aruba Networking CX 6300L 24p Smart Rate 1G/2.5G/5G/10G CL6 2p SFP56 50G 2p SFP28 25G L2 Switch (S3L75A)
Differentiator	Non-PoE	Class 4 PoE/PoE+	Non-PoE TAA certified	Class 4 PoE/PoE+ TAA certified	Layer 2 only L switch does not support Layer 3 features in the F and M models Non-PoE
Power consumption	Idle: 52W 100% Traffic Rate: 74W	Idle: 63W 100% Traffic Rate: 86W	Idle: 52W 100% Traffic Rate: 74W	Idle: 63W 100% Traffic Rate: 86W	With JL086A PSU: Hibernation (0 rpm fan): 37W Idle: 90W 100% Traffic Rate: 143W With JL087A PSU: Hibernation (0 rpm fan): 41W Idle: 90W 100% Traffic Rate: 140W With JL670A PSU: Hibernation (0 rpm fan): 35W Idle: 101W 100% Traffic Rate: 152W
Input voltage	Fixed PSU: 100V–120V/200V–240V	Fixed PSU: 100V–120V/200V–240V	Fixed PSU: 100V120V/200V240V	Fixed PSU: 100V120V/200V240V	JL670A PSU: 110V–120V/208V–240V JL086A PSU: 100V–240V JL087A PSU: 110V–240V

	HPE Aruba Networking CX 6300F 48-port 1GbE and 4-port SFP56 Switch (JL667A)	HPE Aruba Networking CX 6300F 48-port 1GbE Class 4 PoE and 4-port SFP56 Switch (JL665A)	HPE Aruba Networking CX 6300F 48p 10M/100M/1G 4p SFP56 50G TAA Switch (SOG97A)	HPE Aruba Networking CX 6300F 48p 10M/100M/1G Class4 PoE 4p SFP56 50G TAA Switch (SOG95A)	HPE Aruba Networking CX 6300L 24p Smart Rate 1G/2.5G/5G/10G CL6 2p SFP56 50G 2p SFP28 25G L2 Switch (S3L75A)
Ports	48 x 10/100/1000 BaseT ports 4 x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port	48 x 10/100/1000 BaseT PoE+ ports supporting up to 30W per port 4 x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port	48x 10/100/1000 BaseT ports 4x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on S0E91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.	48x 10/100/1000 BaseT PoE+ ports supporting up to 30W per port 4x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on S0E91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.	24x HPE Smart Rate 100M [5]/1G/2.5G/5G BaseT Class 6 PoE ports supporting up to 60W per port 4x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at and 802.3bt (up to 60W) 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on S0E91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports. [5] 100M use on HPE Smart Rate ports is limited to full duplex only. For 100M half duplex support, use 1G ports on other models.
Latency	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 4.24 s 10 Gbps: 1.50 s 25 Gbps: 2.91 s 50 Gbps: 3.49 s
Switching capacity	496 Gbps	496 Gbps	496 Gbps	496 Gbps	780 Gbps

	HPE Aruba Networking CX 6300F 48-port 1GbE and 4-port SFP56 Switch (JL667A)	HPE Aruba Networking CX 6300F 48-port 1GbE Class 4 PoE and 4-port SFP56 Switch (JL665A)	HPE Aruba Networking CX 6300F 48p 10M/100M/1G 4p SFP56 50G TAA Switch (SOG97A)	HPE Aruba Networking CX 6300F 48p 10M/100M/1G Class4 PoE 4p SFP56 50G TAA Switch (SOG95A)	HPE Aruba Networking CX 6300L 24p Smart Rate 1G/2.5G/5G/10G CL6 2p SFP56 50G 2p SFP28 25G L2 Switch (S3L75A)
Stacking capabilities	Up to 10 members per stack. Note: CX 6300L switches only stack with other CX 6300L switches				
Throughput	369 Mpps	369 Mpps	369 Mpps	369 Mpps	580 Mpps
Memory and processor	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	Quad Core Arm® Cortex® A72 @ 1.8GHz, 8 GB DDR4, 32 GB eMMC 16 MB Shared Packet Buffer Memory
Power supply	Internal (fixed) power supply (200W)	Internal (fixed) power supply (950W)	Internal (fixed) power supply (200W)	Internal (fixed) power supply (950W)	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A.
PoE capability		Maximum PoE power: 740W		Maximum PoE power: 740W	Maximum PoE power:2880W
Management features	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software	1 default VRF, 1 management VRF
Operating temperature	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5000 ft. Derate 1°C for every 1000 ft from 5000 ft to 10000 ft.

	HPE Aruba Networking CX 6300F 48-port 1GbE and 4-port SFP56 Switch (JL667A)	HPE Aruba Networking CX 6300F 48-port 1GbE Class 4 PoE and 4-port SFP56 Switch (JL665A)	HPE Aruba Networking CX 6300F 48p 10M/100M/1G 4p SFP56 50G TAA Switch (SOG97A)	HPE Aruba Networking CX 6300F 48p 10M/100M/1G Class4 PoE 4p SFP56 50G TAA Switch (SOG95A)	HPE Aruba Networking CX 6300L 24p Smart Rate 1G/2.5G/5G/10G CL6 2p SFP56 50G 2p SFP28 25G L2 Switch (S3L75A)
--	---	---	--	---	--

Warranty

Limited lifetime warranty. See warranty details.

	HPE Aruba Networking CX 6300L 48p Smart Rate 100M/1G/2.5G/5G CL8 2p SFP56 50G 2p SFP28 25G L2 Switch (S3L76A)	HPE Aruba Networking CX 6300M 12p CL8 PoE 36p CL6 PoE Smart Rate 1G/2.5G/5G 2p 50G 2p 10G Switch (R8S91A)	HPE Aruba Networking CX 6300M 24-port 1GbE and 4-port SFP56 Switch (JL664A)	HPE Aruba Networking CX 6300M 24-port 1GbE Class 4 PoE and 4-port SFP56 Switch (JL662A)	HPE Aruba Networking CX 6300M 24-port HPE Smart Rate 1/2.5/5GbE Class 6 PoE and 4-port SFP56 Switch (JL660A)
Differentiator	Layer 2 only L switch does not support Layer 3 features in the F and M models Non-PoE	Class 4 PoE/PoE+	Non-PoE	Class 4 PoE/PoE+	Class 4 PoE/PoE+
Power consumption	With JL086A PSU: Hibernation (0 rpm fan): 43W Idle: 104W 100% Traffic Rate: 173W With JL087A PSU: Hibernation (0 rpm fan): 41W Idle: 104W 100% Traffic Rate: 173W With JL670A PSU: Hibernation (0 rpm fan): 37W Idle: 115W 100% Traffic Rate: 184W	With JL086A PSU: Idle: 70W 100% Traffic Rate: 90W With JL087A PSU: Idle: 71W 100% Traffic Rate: 88W With JL670A PSU: Idle: 73W 100% Traffic Rate: 96W	Idle: 49W 100% Traffic Rate: 64W	With JL086A PSU: Idle: 60W 100% Traffic Rate: 76W With JL087A PSU: Idle: 59W 100% Traffic Rate: 74W With JL670A PSU: Idle: 62W 100% Traffic Rate: 81W	With JL086A PSU: Idle: 93W 100% Traffic Rate: 137W With JL087A PSU: Idle: 91W 100% Traffic Rate: 131W With JL670A PSU: Idle: 98W 100% Traffic Rate: 139W
Input voltage	JL670A PSU: 110V–120V/208V–240V JL086A PSU: 100V–240V JL087A PSU: 110V–240V	JL670A PSU: 110V–120V/208V–240V JL086A PSU: 100V–240V JL087A PSU: 110V–240V	JL085A PSU: 100V–240V	JL670A PSU: 110V–120V/208V–240V JL086A PSU: 100V–240V JL087A PSU: 110V–240V	JL670A PSU: 110V–120V/208V–240V JL086A PSU: 100V–240V JL087A PSU: 110V–240V

	HPE Aruba Networking CX 6300L 48p Smart Rate 100M/1G/2.5G/5G CL8 2p SFP56 50G 2p SFP28 25G L2 Switch (S3L76A)	HPE Aruba Networking CX 6300M 12p CL8 PoE 36p CL6 PoE Smart Rate 1G/2.5G/5G 2p 50G 2p 10G Switch (R8S91A)	HPE Aruba Networking CX 6300M 24-port 1GbE and 4-port SFP56 Switch (JL664A)	HPE Aruba Networking CX 6300M 24-port 1GbE Class 4 PoE and 4-port SFP56 Switch (JL662A)	HPE Aruba Networking CX 6300M 24-port HPE Smart Rate 1/2.5/5GbE Class 6 PoE and 4-port SFP56 Switch (JL660A)
Ports	48x HPE Smart Rate 100M [5]/1G/2.5G/5G BaseT Class 6 PoE ports supporting up to 60W per port 4x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at and 802.3bt (up to 60W) 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on SOE91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports. [5] 100M use on HPE Smart Rate ports is limited to full duplex only. For 100M half duplex support, use 1G ports on other models.	48 x 10/100/1000 BaseT PoE+ ports supporting up to 30W per port 4 x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port	24 x 10/100/1000 BaseT ports 4 x 1G/10G/25G/50G [4] SFP ports 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port	24 x 10/100/1000 BaseT PoE+ ports supporting up to 30W per port 4 x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port	24 x HPE Smart Rate 100 M [5]/1G/2.5G/5G BaseT Class 6 PoE ports supporting up to 60W per port 4 x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at and 802.3bt (up to 60W) 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port
Latency	1 Gbps: 4.24 s 10 Gbps: 1.50 s 25 Gbps: 2.91 s 50 Gbps: 3.49 s	1 Gbps: 4.24 s 10 Gbps: 1.50 s 25 Gbps: 2.91 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s
Switching capacity	780 Gbps	496 Gbps	448 Gbps	448 Gbps	640 Gbps

	HPE Aruba Networking CX 6300L 48p Smart Rate 100M/1G/2.5G/5G CL8 2p SFP56 50G 2p SFP28 25G L2 Switch (S3L76A)	HPE Aruba Networking CX 6300M 12p CL8 PoE 36p CL6 PoE Smart Rate 1G/2.5G/5G 2p 50G 2p 10G Switch (R8S91A)	HPE Aruba Networking CX 6300M 24-port 1GbE and 4-port SFP56 Switch (JL664A)	HPE Aruba Networking CX 6300M 24-port 1GbE Class 4 PoE and 4-port SFP56 Switch (JL662A)	HPE Aruba Networking CX 6300M 24-port HPE Smart Rate 1/2.5/5GbE Class 6 PoE and 4-port SFP56 Switch (JL660A)
Stacking capabilities	Up to 10 members per stack. Note: CX 6300L switches only stack with other CX 6300L switches				
Throughput	580 Mpps	369 Mpps	334 Mpps	334 Mpps	476 Mpps
Memory and processor	Quad Core Arm® Cortex® A72 @ 1.8GHz, 8 GB DDR4, 32 GB eMMC 16 MB Shared Packet Buffer Memory	Quad Core Arm Cortex™ A72 @ 1.8GHz, 8 GB DDR4, 32 GB eMMC 16 MB Shared Packet Buffer Memory	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration
Power supply	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supports JL085A PSU.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A.
PoE capability	Maximum PoE power: 2880W	Maximum PoE power: 1440W		Maximum PoE power: 720W	Maximum PoE power: 1440W
Management features	1 default VRF, 1 management VRF	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software

	HPE Aruba Networking CX 6300L 48p Smart Rate 100M/1G/2.5G/5G CL8 2p SFP56 50G 2p SFP28 25G L2 Switch (S3L76A)	HPE Aruba Networking CX 6300M 12p CL8 PoE 36p CL6 PoE Smart Rate 1G/2.5G/5G 2p 50G 2p 10G Switch (R8S91A)	HPE Aruba Networking CX 6300M 24-port 1GbE and 4-port SFP56 Switch (JL664A)	HPE Aruba Networking CX 6300M 24-port 1GbE Class 4 PoE and 4-port SFP56 Switch (JL662A)	HPE Aruba Networking CX 6300M 24-port HPE Smart Rate 1/2.5/5GbE Class 6 PoE and 4-port SFP56 Switch (JL660A)
Operating temperature	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate -1 degree C for every 1,000 ft from 5,000 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time. No more than 96 consecutive hours and no more than 360 hours total (15 days) in 1 year.	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5000 ft. Derate 1°C for every 1000 ft from 5000 ft to 10000 ft. Can support excursion to 131°F (55°C) for short periods of time [3]. Requires two fan trays to support excursion.
Warranty	Limited lifetime warranty. See warranty details.				

	HPE Aruba Networking CX 6300M 24-port SFP+ and 4-port SFP56 Switch (JL658A)	HPE Aruba Networking CX 6300M 24p 10M/100M/1G 4p SFP56 50G TAA Switch (SOG01A)	HPE Aruba Networking CX 6300M 24p 10M/100M/1G Class4 PoE 4p SFP56 50G TAA Switch (SOF99A)	HPE Aruba Networking CX 6300M 24p SFP 1G 2p SFP56 50G 2p SFP28 25G MACsec Switch (S4P44A)	HPE Aruba Networking CX 6300M 24p SFP 1G 2p SFP56 50G 2p SFP28 25G MACsec TAA Switch (S4P48A)
Differentiator	Non-PoE	Non-PoE TAA certified	Class 4 PoE/PoE+ TAA certified	Non-PoE	Non-PoE TAA certified
Power consumption	Idle: 51W 100% Traffic Rate: 85W	Idle: 49W 100% Traffic Rate: 64W	With JL086A PSU: Idle: 60W 100% Traffic Rate: 76W With JL087A PSU: Idle: 59W 100% Traffic Rate: 74W With JL670A PSU: Idle: 62W 100% Traffic Rate: 81W	With JL086A PSU: Idle: 133W 100% Traffic Rate: 199W With JL087A PSU: Idle: 138W 100% Traffic Rate: 193W With JL670A PSU: Idle: 140W 100% Traffic Rate: 201W	Idle: 51W 100% Traffic Rate: 85W
Input voltage	JL085A PSU: 100V–240V	JL085A PSU: 100V–240V	JL670A PSU: 110V–120V/208V–240V JL086A PSU: 100V–240V JL087A PSU: 110V–240V	JL670A PSU: 110V–120V/208V–240V JL086A PSU: 100V–240V JL087A PSU: 110V–240V	JL085A PSU: 100V–240V

	HPE Aruba Networking CX 6300M 24-port SFP+ and 4-port SFP56 Switch (JL658A)	HPE Aruba Networking CX 6300M 24p 10M/100M/1G 4p SFP56 50G TAA Switch (SOG01A)	HPE Aruba Networking CX 6300M 24p 10M/100M/1G Class4 PoE 4p SFP56 50G TAA Switch (SOF99A)	HPE Aruba Networking CX 6300M 24p SFP 1G 2p SFP56 50G 2p SFP28 25G MACsec Switch (S4P44A)	HPE Aruba Networking CX 6300M 24p SFP 1G 2p SFP56 50G 2p SFP28 25G MACsec TAA Switch (S4P48A)
Ports	24 x 1G/10G SFP+ ports 4 x 1G/10G/25G/50G [4] SFP ports 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port	24-port 10/100/1000 BaseT ports 4x 1G/10G/25G/50G [4] SFP ports 1x USBC Console Port 1x OOBM port 1x USB Type A Host port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on SOE91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.	24x 10/100/1000 BaseT PoE+ ports supporting up to 30W per port 4x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on SOE91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.	48x HPE Smart Rate 100M [5]/1G/2.5G/5G BaseT Class 6 PoE ports supporting up to 60W per port 4x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at and 802.3bt (up to 60W) 1x USB-C console port 1x USB Type-A host port 1x OOBM port [5] 100M use on HPE Smart Rate ports is limited to full duplex only. For 100M half duplex support, use 1G ports on other models. [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on SOE91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.	24x 1G/10G SFP+ ports 4x 1G/10G/25G/50G [4] SFP ports 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on SOE91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.
Latency	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 4.24 s 10 Gbps: 1.50 s 25 Gbps: 2.91 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s
Switching capacity	880 Gbps	448 Gbps	448 Gbps	880 Gbps	880 Gbps

	HPE Aruba Networking CX 6300M 24-port SFP+ and 4-port SFP56 Switch (JL658A)	HPE Aruba Networking CX 6300M 24p 10M/100M/1G 4p SFP56 50G TAA Switch (SOG01A)	HPE Aruba Networking CX 6300M 24p 10M/100M/1G Class4 PoE 4p SFP56 50G TAA Switch (SOF99A)	HPE Aruba Networking CX 6300M 24p SFP 1G 2p SFP56 50G 2p SFP28 25G MACsec Switch (S4P44A)	HPE Aruba Networking CX 6300M 24p SFP 1G 2p SFP56 50G 2p SFP28 25G MACsec TAA Switch (S4P48A)
Stacking capabilities	Up to 10 members per stack. Note: CX 6300L switches only stack with other CX 6300L switches				
Throughput	654 Mpps	334 Mpps	334 Mpps	654 Mpps	654 Mpps
Memory and processor	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration				
Power supply	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supports JL085A PSU.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supports JL085A PSU.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A.	2 field-replaceable, hot-swappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL085A and JL757A.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supports JL085A PSU.
PoE capability	##BL##BLANK##ANK##		Maximum PoE power: 720W	Maximum PoE power: 2880W	
Management features	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software				
Operating temperature	32°F to 113°F (0°C to 45°C) up to 5000 ft. Derate 1°C for every 1000 ft from 5000 ft to 10000 ft. Can support excursion to 131°F (55°C) for short periods of time [3]. Operating temperature is reduced to 32°F (0°C) to 104°F (40°C) up to 5000 ft when 10 G SFP+ LR or ER transceivers are installed.	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5000 ft. Derate 1°C for every 1000 ft from 5000 ft to 10000 ft. Can support excursion to 131°F (55°C) for short periods of time [3]. Operating temperature is reduced to 32°F (0°C) to 104°F (40°C) up to 5000 ft when 10G SFP+ LR or ER transceivers are installed.
Warranty	Limited lifetime warranty. See warranty details.				

	HPE Aruba Networking CX 6300M 24p SFP+ 1G/10G 4p SFP56 50G 2xFan PSU Bundle (S5Z46A)	HPE Aruba Networking CX 6300M 24p SFP+ 1G/10G 4p SFP56 50G TAA Switch (SOG03A)	HPE Aruba Networking CX 6300M 24p SFP+ LRM support and 2p 50G and 2p 25G MACSec Switch (R8S92A)	HPE Aruba Networking CX 6300M 24p Smart Rate 1G/2.5G/5G Class6 PoE 4p SFP56 50G TAA Switch (SOG05A)	HPE Aruba Networking CX 6300M 24p Smart Rate 1G/2.5G/5G/10G Class6 PoE 2p 50G 2p 25G Switch (R8S89A)
Differentiator	Non-PoE	Non-PoE TAA certified	Non-PoE	Class 4 PoE/PoE+ TAA certified	Class 4 PoE/PoE+
Power consumption	Idle: 51W 100% Traffic Rate: 85W	Idle: 51W 100% Traffic Rate: 85W	With JL086A PSU: Idle: 60W 100% Traffic Rate: 76W With JL087A PSU: Idle: 59W 100% Traffic Rate: 74W With JL670A PSU: Idle: 62W 100% Traffic Rate: 81W	With JL086A PSU: Idle: 93W 100% Traffic Rate: 137W With JL087A PSU: Idle: 91W 100% Traffic Rate: 131W With JL670A PSU: Idle: 98W 100% Traffic Rate: 139W	With JL086A PSU: Idle: 93W 100% Traffic Rate: 137W With JL087A PSU: Idle: 91W 100% Traffic Rate: 131W With JL670A PSU: Idle: 98W 100% Traffic Rate: 139W
Heat dissipation	Max: 853 BTU/hr Idle: 174 BTU/hr				
Input voltage	JL085A PSU: 100V–240V	JL085A PSU: 100V–240V	JL670A PSU: 110V–120V/208V–240V JL086A PSU: 100V–240V JL087A PSU: 110V–240V	JL670A PSU: 110V–120V/208V–240V JL086A PSU: 100V–240V JL087A PSU: 110V–240V	JL670A PSU: 110V–120V/208V–240V JL086A PSU: 100V–240V JL087A PSU: 110V–240V

	HPE Aruba Networking CX 6300M 24p SFP+ 1G/10G 4p SFP56 50G 2xFan PSU Bundle (S5Z46A)	HPE Aruba Networking CX 6300M 24p SFP+ 1G/10G 4p SFP56 50G TAA Switch (SOG03A)	HPE Aruba Networking CX 6300M 24p SFP+ LRM support and 2p 50G and 2p 25G MACSec Switch (R8S92A)	HPE Aruba Networking CX 6300M 24p Smart Rate 1G/2.5G/5G Class6 PoE 4p SFP56 50G TAA Switch (SOG05A)	HPE Aruba Networking CX 6300M 24p Smart Rate 1G/2.5G/5G/10G Class6 PoE 2p 50G 2p 25G Switch (R8S89A)
Ports	24x 1G/10G SFP+ ports 4x 1G/10G/25G/50G [4] SFP ports 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on SOE91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.	24x 1G/10G SFP+ ports 4x 1G/10G/25G/50G [4] SFP ports 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on SOE91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.	24 x 10/100/1000 BaseT PoE+ ports supporting up to 30W per port 4 x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port	24x HPE Smart Rate 100M [5]/1G/2.5G/5G BaseT Class 6 PoE ports supporting up to 60W per port 4x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at and 802.3bt (up to 60W) 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on SOE91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports. [5] 100M use on HPE Smart Rate ports is limited to full duplex only. For 100M half duplex support, use 1G ports on other models.	24 x HPE Smart Rate 100 M [5]/1G/2.5G/5G BaseT ports Class 6 PoE ports supporting up to 60W per port 4 x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at and 802.3bt (up to 60W) 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port
Latency	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 4.24 s 10 Gbps: 1.50 s 25 Gbps: 2.91 s 50 Gbps: 3.49 s	1 Gbps: 4.24 s 10 Gbps: 1.50 s 25 Gbps: 2.91 s 50 Gbps: 3.49 s	1 Gbps: 4.24 s 10 Gbps: 1.50 s 25 Gbps: 2.91 s 50 Gbps: 3.49 s
Switching capacity	880 Gbps	880 Gbps	448 Gbps	640 Gbps	640 Gbps

	HPE Aruba Networking CX 6300M 24p SFP+ 1G/10G 4p SFP56 50G 2xFan PSU Bundle (S5Z46A)	HPE Aruba Networking CX 6300M 24p SFP+ 1G/10G 4p SFP56 50G TAA Switch (SOG03A)	HPE Aruba Networking CX 6300M 24p SFP+ LRM support and 2p 50G and 2p 25G MACSec Switch (R8S92A)	HPE Aruba Networking CX 6300M 24p Smart Rate 1G/2.5G/5G Class6 PoE 4p SFP56 50G TAA Switch (SOG05A)	HPE Aruba Networking CX 6300M 24p Smart Rate 1G/2.5G/5G/10G Class6 PoE 2p 50G 2p 25G Switch (R8S89A)
Stacking capabilities	Up to 10 members per stack. Note: CX 6300L switches only stack with other CX 6300L switches				
Throughput	654 Mpps	654 Mpps	334 Mpps	476 Mpps	476 Mpps
Memory and processor	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	Quad Core Arm Cortex™ A72 @ 1.8GHz, 8 GB DDR4, 32 GB eMMC 16 MB Shared Packet Buffer Memory	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	Quad Core Arm Cortex™ A72 @ 1.8GHz, 8 GB DDR4, 32 GB eMMC 16 MB Shared Packet Buffer Memory
Power supply	2 fieldreplaceable, hotswappable power supply slots	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supports JL085A PSU.	2 field-replaceable, hot-swappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL085A and JL757A.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A.
PoE capability			Maximum PoE power: 720W	Maximum PoE power: 1440W	Maximum PoE power: 1440W
Management features	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software				

	HPE Aruba Networking CX 6300M 24p SFP+ 1G/10G 4p SFP56 50G 2xFan PSU Bundle (S5Z46A)	HPE Aruba Networking CX 6300M 24p SFP+ 1G/10G 4p SFP56 50G TAA Switch (SOG03A)	HPE Aruba Networking CX 6300M 24p SFP+ LRM support and 2p 50G and 2p 25G MACSec Switch (R8S92A)	HPE Aruba Networking CX 6300M 24p Smart Rate 1G/2.5G/5G Class6 PoE 4p SFP56 50G TAA Switch (SOG05A)	HPE Aruba Networking CX 6300M 24p Smart Rate 1G/2.5G/5G/10G Class6 PoE 2p 50G 2p 25G Switch (R8S89A)
Operating temperature	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5000 ft. Derate 1°C for every 1000 ft from 5000 ft to 10000 ft. Can support excursion to 131°F (55°C) for short periods of time [3]. Operating temperature is reduced to 32°F (0°C) to 104°F (40°C) up to 5000 ft when 10G SFP+ LR or ER transceivers are installed.	32°F to 113°F (0°C to 45°C) up to 5000 ft. Derate 1°C for every 1000 ft from 5000 ft to 10000 ft. Can support excursion to 131°F (55°C) for short periods of time [3]. 55°C excursion not supported when 10 G LRM/LR/ER inserted. When 10 G BT and 10 G LRM/LR/ER transceivers are installed together, fan redundancy is only supported up to 104°F (40°C) 5000 ft.	32°F to 113°F (0°C to 45°C) up to 5000 ft. Derate 1°C for every 1000 ft from 5000 ft to 10000 ft. Can support excursion to 131°F (55°C) for short periods of time [3]. Requires two fan trays to support excursion.	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].
Warranty	Limited lifetime warranty. See warranty details.				

	HPE Aruba Networking CX 6300M 32p 1G 16p SmtRt 5G Class8 PoE 2p SFP56 50G 2p SFP28 25G MACsec Switch (S4P41A)	HPE Aruba Networking CX 6300M 32p 1G 16p SmtRt 5G Class8 PoE 2p SFP56 50G 2p SFP28 25G MACsec TAA Sw (S4P45A)	HPE Aruba Networking CX 6300M 32p SmtRt 5G 8p SFP+ 10G LRM 2p SFP56 50G 2p SFP28 25G MACsec TAA Sw (S4P46A)	HPE Aruba Networking CX 6300M 32p SmtRt 5G CL8 8p SFP+ 10G LRM 2p SFP56 50G 2p SFP28 25G MACsec Sw (S4P42A)	HPE Aruba Networking CX 6300M 48-port 1GbE and 4-port SFP56 Switch (JL663A)
Differentiator	Class 4 PoE/PoE+	Class 4 PoE/PoE+ TAA certified	Non-PoE TAA certified	Non-PoE	Non-PoE
Power consumption	With JL670A PSU: Idle: 103W 100% Traffic Rate: 134W With JL758A PSU: Idle: 111W 100% Traffic Rate: 135W	With JL086A PSU: Idle: 60W 100% Traffic Rate: 76W With JL087A PSU: Idle: 59W 100% Traffic Rate: 74W With JL670A PSU: Idle: 62W 100% Traffic Rate: 81W	Idle: 56W 100% Traffic Rate: 75W	With JL670A PSU: Idle: 106W 100% Traffic Rate: 159W With JL758A PSU: Idle: 118W 100% Traffic Rate: 156W	Idle: 56W 100% Traffic Rate: 75W
Input voltage	JL670A PSU: 110V–120V/200V/208V–240V; AC input JL086A PSU: 100V–240V; AC input JL087A PSU: 110V–240V; AC input JL758A PSU: 36–72V; DC input	JL670A PSU: 110V–120V/208V–240V JL086A PSU: 100V–240V JL087A PSU: 110V–240V	JL085A PSU: 100V–240V	JL670A PSU: 110V–120V/200V/208V–240V; AC input JL086A PSU: 100V–240V; AC input JL087A PSU: 110V–240V; AC input JL758A PSU: 36–72V; DC input	JL085A PSU: 100V–240V

HPE Aruba Networking CX 6300M 32p 1G 16p SmtRt 5G Class8 PoE 2p SFP56 50G 2p SFP28 25G MACsec Switch (S4P41A)	HPE Aruba Networking CX 6300M 32p 1G 16p SmtRt 5G Class8 PoE 2p SFP56 50G 2p SFP28 25G MACsec TAA Sw (S4P45A)	HPE Aruba Networking CX 6300M 32p SmtRt 5G 8p SFP+ 10G LRM 2p SFP56 50G 2p SFP28 25G MACsec TAA Sw (S4P46A)	HPE Aruba Networking CX 6300M 32p SmtRt 5G CL8 8p SFP+ 10G LRM 2p SFP56 50G 2p SFP28 25G MACsec Sw (S4P42A)	HPE Aruba Networking CX 6300M 48-port 1GbE and 4-port SFP56 Switch (JL663A)
---	---	---	---	---

Ports

32x 10/100/1000M and 16x HPE Smart Rate 1/2.5/5G BaseT ports (configuration can be changed to 8x HPE Smart Rate 10G BaseT ports) with Class 8 PoE supporting up to 90W per port
2x 10G/25G/50G [4] SFP ports
2x 10G/25G SFP ports (MACsec)
Supports PoE standards IEEE 802.3af, 802.3at and 802.3bt (up to 90W)

1x USB-C console port
1x USB Type-A host port
1x OOBM port
1x RJ-45 console Port
1x Bluetooth dongle to be used with CX Mobile App

[4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on S0E91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.

24x 10/100/1000 BaseT PoE+ ports supporting up to 30W per port
4x 1G/10G/25G/50G [4] SFP ports
Supports PoE standards IEEE 802.3af, 802.3at

1x USB-C console port
1x USB Type-A host port
1x OOBM port

[4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on S0E91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.

48x 10/100/1000 BaseT ports
4x 1G/10G/25G/50G [4] SFP ports

1x USB-C console port
1x USB Type-A host port
1x OOBM port

[4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on S0E91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.

32x HPE Smart Rate 1G/2.5G/5G Base-T (configuration can be changed to 16x HPE Smart Rate 1G/2.5G/5G Base-T and 8x HPE Smart Rate 1G/2.5G/5G/10G Base-T ports) Class 8 PoE ports supporting up to 90W POE per port and 8x 1G/10G SFP+ (LRM) ports
2x 10G/25G/50G [4] SFP ports
2x 10G/25G SFP ports (MACsec)
Supports PoE standards IEEE 802.3af, 802.3at and 802.3bt (up to 90W)

1x USB-C console port
1x USB Type-A host port
1x OOBM port
1x RJ-45 console Port
1x Bluetooth dongle to be used with CX Mobile App

[4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on S0E91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.

48 x 10/100/1000 BaseT ports
4 x 1G/10G/25G/50G [4] SFP ports

1 x USB-C console port
1 x USB Type-A host port
1 x OOBM port

	HPE Aruba Networking CX 6300M 32p 1G 16p SmtRt 5G Class8 PoE 2p SFP56 50G 2p SFP28 25G MACsec Switch (S4P41A)	HPE Aruba Networking CX 6300M 32p 1G 16p SmtRt 5G Class8 PoE 2p SFP56 50G 2p SFP28 25G MACsec TAA Sw (S4P45A)	HPE Aruba Networking CX 6300M 32p SmtRt 5G 8p SFP+ 10G LRM 2p SFP56 50G 2p SFP28 25G MACsec TAA Sw (S4P46A)	HPE Aruba Networking CX 6300M 32p SmtRt 5G CL8 8p SFP+ 10G LRM 2p SFP56 50G 2p SFP28 25G MACsec Sw (S4P42A)	HPE Aruba Networking CX 6300M 48-port 1GbE and 4-port SFP56 Switch (JL663A)
Latency	Less than 5 μ s 1 Gbps: 3.6 μ s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	Less than 5 μ s 10 Gbps LRM: 2.3 μ s 10 Gbps dual mode ports: 5.5 μ s 25 Gbps: 3.5 μ s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s
Switching capacity	524 Gbps	448 Gbps	496 Gbps	780 Gbps	496 Gbps
Stacking capabilities	Up to 10 members per stack. Note: CX 6300L switches only stack with other CX 6300L switches				
Throughput	390 Mpps	334 Mpps	369 Mpps	580 Mpps	369 Mpps
Memory and processor	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration				
Power supply	2 field-replaceable, hot-swappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A, JL670A and JL758A.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supports JL085A PSU.	2 field-replaceable, hot-swappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A, JL670A and JL758A.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supports JL085A PSU.
PoE capability	Maximum PoE power: 2880W	Maximum PoE power: 720W	Maximum PoE power: 2880W	Maximum PoE power: 2880W	
Management features	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software				
Operating temperature	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].				
Warranty	Limited lifetime warranty. See warranty details.				

	HPE Aruba Networking CX 6300M 48-port 1GbE Class 4 PoE and 4-port SFP56 Switch (JL661A)	HPE Aruba Networking CX 6300M 48-port HPE Smart Rate 1/2.5/5GbE Class 6 PoE and 4-port SFP56 Switch (JL659A)	HPE Aruba Networking CX 6300M 48G Power-to-Port Airflow 2 Fans 1 Power Supply Unit Bundle (R9F63A)	HPE Aruba Networking CX 6300M 48p 10M/100M/1G 4p SFP56 50G Power-to-Port 2xFan PSU TAA Bundle (SOG02A)	HPE Aruba Networking CX 6300M 48p 10M/100M/1G 4p SFP56 50G TAA Switch (SOG00A)
Differentiator	Class 4 PoE/PoE+	Class 4 PoE/PoE+	Non-PoE	Non-PoE TAA certified	Non-PoE TAA certified
Power consumption	With JLO86A PSU: Idle: 70W 100% Traffic Rate: 90W With JLO87A PSU: Idle: 71W 100% Traffic Rate: 88W With JL670A PSU: Idle: 73W 100% Traffic Rate: 96W	With JLO86A PSU: Idle: 133W 100% Traffic Rate: 199W With JLO87A PSU: Idle: 138W 100% Traffic Rate: 193W With JL670A PSU: Idle: 140W 100% Traffic Rate: 201W	Idle: 56W 100% Traffic Rate: 75W	Idle: 56W 100% Traffic Rate: 75W	Idle: 56W 100% Traffic Rate: 75W
Input voltage	JL670A PSU: 110V–120V/208V–240V JLO86A PSU: 100V–240V JLO87A PSU: 110V–240V	JL670A PSU: 110V–120V/208V–240V JLO86A PSU: 100V–240V JLO87A PSU: 110V–240V	JL760A PSU: 100V–240V	JL760A PSU: 100V–240V	JLO85A PSU: 100V/240V
Ports	48 x 10/100/1000 BaseT PoE+ ports supporting up to 30W per port 4 x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port	48 x HPE Smart Rate 100 M [5]/1G/2.5G/5G BaseT Class 6 PoE ports supporting up to 60W per port 4 x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at and 802.3bt (up to 60W) 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port	48 x 10/100/1000 BaseT ports 4 x 1G/10G/25G/50G [4] SFP ports 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port	48x 10/100/1000 BaseT ports 4x 1G/10G/25G/50G [4] SFP ports 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on SOE91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.	48x 10/100/1000 BaseT ports 4x 1G/10G/25G/50G [4] SFP ports 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on SOE91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.

	HPE Aruba Networking CX 6300M 48-port 1GbE Class 4 PoE and 4-port SFP56 Switch (JL661A)	HPE Aruba Networking CX 6300M 48-port HPE Smart Rate 1/2.5/5GbE Class 6 PoE and 4-port SFP56 Switch (JL659A)	HPE Aruba Networking CX 6300M 48G Power-to-Port Airflow 2 Fans 1 Power Supply Unit Bundle (R9F63A)	HPE Aruba Networking CX 6300M 48p 10M/100M/1G 4p SFP56 50G Power-to-Port 2xFan PSU TAA Bundle (SOG02A)	HPE Aruba Networking CX 6300M 48p 10M/100M/1G 4p SFP56 50G TAA Switch (SOG00A)
Latency	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s				
Switching capacity	496 Gbps	880 Gbps	496 Gbps	496 Gbps	496 Gbps
Stacking capabilities	Up to 10 members per stack. Note: CX 6300L switches only stack with other CX 6300L switches				
Throughput	369 Mpps	654 Mpps	369 Mpps	369 Mpps	369 Mpps
Memory and processor	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration				
Power supply	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A.	2 fieldreplaceable, hotswappable power supply slots	2 Fieldreplaceable, hotswappable powersupply slots and comes with one power-to-port powersupply preinstalled. Additional power-to-port powersupply can be ordered separately. Supports JL760A power-to-port powersupply only.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supports JL085A PSU.
PoE capability	Maximum PoE power: 1440W	Maximum PoE power: 2880W			##BLAN##BLANK##K##
Management features	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software				

	HPE Aruba Networking CX 6300M 48-port 1GbE Class 4 PoE and 4-port SFP56 Switch (JL661A)	HPE Aruba Networking CX 6300M 48-port HPE Smart Rate 1/2.5/5GbE Class 6 PoE and 4-port SFP56 Switch (JL659A)	HPE Aruba Networking CX 6300M 48G Power-to-Port Airflow 2 Fans 1 Power Supply Unit Bundle (R9F63A)	HPE Aruba Networking CX 6300M 48p 10M/100M/1G 4p SFP56 50G Power-to-Port 2xFan PSU TAA Bundle (SOG02A)	HPE Aruba Networking CX 6300M 48p 10M/100M/1G 4p SFP56 50G TAA Switch (SOG00A)
Operating temperature	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5000 ft. Derate 1°C for every 1000 ft from 5000 ft to 10000 ft.	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5000 ft. Derate 1°C for every 1000 ft from 5000 ft to 10000 ft.	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].
Warranty	Limited lifetime warranty. See warranty details.				

	HPE Aruba Networking CX 6300M 48p 10M/100M/1G Class4 PoE 4p SFP56 50G TAA Switch (SOG06A)	HPE Aruba Networking CX 6300M 48p 1GbE 4p SFP56 Power-to-Port 2 Fan Trays 1 PSU Bundle (JL762A)	HPE Aruba Networking CX 6300M 48p HPE Smart Rate 1G/2.5G/5G Class8 PoE 2p 50G 2p 25G Switch (R8S90A)	HPE Aruba Networking CX 6300M 48p SFP 1G 2p SFP56 50G 2p SFP28 25G MACsec Switch (S4P43A)	HPE Aruba Networking CX 6300M 48p SFP 1G 2p SFP56 50G 2p SFP28 25G MACsec TAA Switch (S4P47A)
Differentiator	Class 4 PoE/PoE+ TAA certified	Non-PoE	Class 4 PoE/PoE+	Non-PoE	Non-PoE TAA certified
Power consumption	With JL086A PSU: Idle: 70W 100% Traffic Rate: 90W With JL087A PSU: Idle: 71W 100% Traffic Rate: 88W With JL670A PSU: Idle: 73W 100% Traffic Rate: 96W	Idle: 56W 100% Traffic Rate: 75W	With JL086A PSU: Idle: 133W 100% Traffic Rate: 199W With JL087A PSU: Idle: 138W 100% Traffic Rate: 193W With JL670A PSU: Idle: 140W 100% Traffic Rate: 201W	With JL085A PSU: Idle: 67W 100% Traffic Rate: 127W With JL757A PSU: Idle: 61W 100% Traffic Rate: 123W	Idle: 49W 100% Traffic Rate: 64W
Input voltage	JL670A PSU: 110V–120V/208V–240V JL086A PSU: 100V–240V JL087A PSU: 110V–240V	JL760A PSU: 100V–240V	JL670A PSU: 110V–120V/208V–240V JL086A PSU: 100V–240V JL087A PSU: 110V–240V	JL085A PSU: 100V–240V; AC input JL757A PSU: 36–72V; DC input	JL085A PSU: 100V–240V

	HPE Aruba Networking CX 6300M 48p 10M/100M/1G Class4 PoE 4p SFP56 50G TAA Switch (S0G06A)	HPE Aruba Networking CX 6300M 48p 1GbE 4p SFP56 Power-to-Port 2 Fan Trays 1 PSU Bundle (JL762A)	HPE Aruba Networking CX 6300M 48p HPE Smart Rate 1G/2.5G/5G Class8 PoE 2p 50G 2p 25G Switch (R8S90A)	HPE Aruba Networking CX 6300M 48p SFP 1G 2p SFP56 50G 2p SFP28 25G MACsec Switch (S4P43A)	HPE Aruba Networking CX 6300M 48p SFP 1G 2p SFP56 50G 2p SFP28 25G MACsec TAA Switch (S4P47A)
Ports	48x 10/100/1000 BaseT PoE+ ports supporting up to 30W per port 4x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on S0E91A and S0X44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.	48 x 10/100/1000 BaseT ports 4 x 1G/10G/25G/50G [4] SFP ports 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port	48 x HPE Smart Rate 100 M [5]/1G/2.5G/5G BaseT Class 6 PoE ports supporting up to 60W per port 4 x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at and 802.3bt (up to 60W) 1 x USB-C console port 1 x USB Type-A host port 1 x OOBM port	48x 1G SFP ports 2x 10G/25G/50G [4] SFP ports 2x 10G/25G SFP ports (MACsec) 1x USB-C console port 1x USB Type-A host port 1x OOBM port	48x 1G SFP ports 2x 10G/25G/50G [4] SFP ports 2x 10G/25G SFP ports (MACsec) 1x USBC Console Port 1x OOBM port 1x USB Type A Host port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on S0E91A and S0X44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports.
Latency	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s	1 Gbps: 4.24 s 10 Gbps: 1.50 s 25 Gbps: 2.91 s 50 Gbps: 3.49 s	1 Gbps: 3.4 μs 50 Gbps: 2.1 μs	1 Gbps: 2.28 s 10 Gbps: 1.46 s 25 Gbps: 1.90 s 50 Gbps: 3.49 s
Switching capacity	496 Gbps	496 Gbps	880 Gbps	396 Gbps	448 Gbps
Stacking capabilities	Up to 10 members per stack. Note: CX 6300L switches only stack with other CX 6300L switches				
Throughput	369 Mpps	369 Mpps	654 Mpps	295 Mpps	334 Mpps

	HPE Aruba Networking CX 6300M 48p 10M/100M/1G Class4 PoE 4p SFP56 50G TAA Switch (SOG06A)	HPE Aruba Networking CX 6300M 48p 1GbE 4p SFP56 Power-to-Port 2 Fan Trays 1 PSU Bundle (JL762A)	HPE Aruba Networking CX 6300M 48p HPE Smart Rate 1G/2.5G/5G Class8 PoE 2p 50G 2p 25G Switch (R8S90A)	HPE Aruba Networking CX 6300M 48p SFP 1G 2p SFP56 50G 2p SFP28 25G MACsec Switch (S4P43A)	HPE Aruba Networking CX 6300M 48p SFP 1G 2p SFP56 50G 2p SFP28 25G MACsec TAA Switch (S4P47A)
Memory and processor	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	Quad Core Arm Cortex™ A72 @ 1.8GHz, 8 GB DDR4, 32 GB eMMC 16 MB Shared Packet Buffer Memory	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration
Power supply	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A.	2 Fieldreplaceable, hotswappable powersupply slots and comes with one power-to-port powersupply preinstalled. Additional power-to-port powersupply can be ordered separately. Supports JL760A power-to-port powersupply only.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A.	2 field-replaceable, hot-swappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL085A and JL757A.	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supports JL085A PSU.
PoE capability	Maximum PoE power: 1440W		Maximum PoE power: 2880W		
Management features	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software				
Operating temperature	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5000 ft. Derate 1°C for every 1000 ft from 5000 ft to 10000 ft.	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].
Warranty	Limited lifetime warranty. See warranty details.				

	HPE Aruba Networking CX 6300M 48p Smart Rate 1G/2.5G/5G Class6 PoE 4p SFP56 50G TAA Switch (SOG04A)	HPE Aruba Networking CX 6300M 48p SR10 1G/2.5G/5G/10G PTP/AVB Class8 PoE and 4p 100G MACsec Switch (SOE91A)	HPE Networking CX6300M 16p 1G 8p Smart Rate 10G Class8 PoE 2p SFP56 50G 2p SFP28 25G Switch (S6X58A)	HPE Networking CX6300M 16p 1G 8p Smart Rate 10G Class8 PoE 2p SFP56 50G 2p SFP28 25G TAA Sw (S7K41A)	HPE Networking CX6300M 24p 1G Class8 PoE 2p SFP56 50G 2p SFP28 25G MACsec Switch (S6X60A)
Differentiator	Class 4 PoE/PoE+ TAA certified	Class 4 PoE/PoE+			
Power consumption	With JL086A PSU: Idle: 133W 100% Traffic Rate: 199W With JL087A PSU: Idle: 138W 100% Traffic Rate: 193W With JL670A PSU: Idle: 140W 100% Traffic Rate: 201W	With single JL086A PSU: Idle: 207W 100% Traffic Rate: 283W With single JL087A PSU: Idle: 208W 100% Traffic Rate: 282W With single JL670A PSU: Idle: 211W 100% Traffic Rate: 283W	Up to 211W depending on model	Up to 211W depending on model	Up to 211W depending on model
Input voltage	JL670A PSU: 110V-120V/208V-240V JL086A PSU: 100V-240V JL087A PSU: 110V-240V	JL670A PSU: 110V-120V/200V/208V-240V; AC input JL086A PSU: 100V-240V; AC input JL087A PSU: 110V-240V; AC input JL758A PSU: 36-72V; DC input	Maximum 120V/208V-240V depending on PSU model	Maximum 120V/208V-240V depending on PSU model	Maximum 120V/208V-240V depending on PSU model

	HPE Aruba Networking CX 6300M 48p Smart Rate 1G/2.5G/5G Class6 PoE 4p SFP56 50G TAA Switch (SOG04A)	HPE Aruba Networking CX 6300M 48p SR10 1G/2.5G/5G/10G PTP/AVB Class8 PoE and 4p 100G MACsec Switch (SOE91A)	HPE Networking CX6300M 16p 1G 8p Smart Rate 10G Class8 PoE 2p SFP56 50G 2p SFP28 25G Switch (S6X58A)	HPE Networking CX6300M 16p 1G 8p Smart Rate 10G Class8 PoE 2p SFP56 50G 2p SFP28 25G TAA Sw (S7K41A)	HPE Networking CX6300M 24p 1G Class8 PoE 2p SFP56 50G 2p SFP28 25G MACsec Switch (S6X60A)
Ports	48x HPE Smart Rate 100M [5]/1G/2.5G/5G BaseT Class 6 PoE ports supporting up to 60W per port 4x 1G/10G/25G/50G [4] SFP ports Supports PoE standards IEEE 802.3af, 802.3at and 802.3bt (up to 60W) 1x USB-C console port 1x USB Type-A host port 1x OOBM port [4] 450G capability is for use with 50G DACs for both interconnect and VSF stacking. 50G transceivers and DACs are not supported on SOE91A and SOX44A switch models, which require QSFP to SFP56 DAC cable for VSF stacking with other CX 6300F and CX 6300M switch models only. VSF stacking not supported on 1G ports. [5] 100M use on HPE Smart Rate ports is limited to fullduplex only. For 100M halfduplex support, use 1G ports on other models.	48x HPE Smart Rate 100M [5]/1G/2.5G/5G/10G BaseT Class 8 PoE ports supporting up to 90W per port (MACsec) 4x 10G/25G/40G/100G QSFP/QSFP28 ports (MACsec) Supports PoE standards IEEE 802.3af, 802.3at and 802.3bt (up to 90W) 1x USB-C console port 1x USB Type-A host port 1x OOBM port 1x RJ-45 console port [5] 100M use on HPE Smart Rate ports is limited to fullduplex only. For 100M halfduplex support, use 1G ports on other models.	16x 1G Copper ports 8x HPE Smart Rate ports (1G/2.5G/5G/10GbE)	16x 1G Copper ports 8x HPE Smart Rate ports (1G/2.5G/5G/10GbE)	24x 1G Copper ports
Latency	1 Gbps: 4.24 s 10 Gbps: 1.50 s 25 Gbps: 2.91 s 50 Gbps: 3.49 s	1 Gbps: 4.24 s 10 Gbps: 1.50 s 25 Gbps: 2.91 s 50 Gbps: 3.49 s	Depending on model	Depending on model	Depending on model
Switching capacity	880 Gbps	1760 Gbps	From to 880 Gbps to 1760 Gbps, depending on model and configuration	From to 880 Gbps to 1760 Gbps, depending on model and configuration	From to 880 Gbps to 1760 Gbps, depending on model and configuration

	HPE Aruba Networking CX 6300M 48p Smart Rate 1G/2.5G/5G Class6 PoE 4p SFP56 50G TAA Switch (SOG04A)	HPE Aruba Networking CX 6300M 48p SR10 1G/2.5G/5G/10G PTP/AVB Class8 PoE and 4p 100G MACsec Switch (SOE91A)	HPE Networking CX6300M 16p 1G 8p Smart Rate 10G Class8 PoE 2p SFP56 50G 2p SFP28 25G Switch (S6X58A)	HPE Networking CX6300M 16p 1G 8p Smart Rate 10G Class8 PoE 2p SFP56 50G 2p SFP28 25G TAA Sw (S7K41A)	HPE Networking CX6300M 24p 1G Class8 PoE 2p SFP56 50G 2p SFP28 25G MACsec Switch (S6X60A)
Stacking capabilities	Up to 10 members per stack. Note: CX 6300L switches only stack with other CX 6300L switches				
Throughput	654 Mpps	1310 Mpps	From to 660 Mpps to 1310 Mpps, depending on model and configuration	From to 660 Mpps to 1310 Mpps, depending on model and configuration	From to 660 Mpps to 1310 Mpps, depending on model and configuration
Memory and processor	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	Quad Core Arm® Cortex® A72 @ 1.8GHz, 8 GB DDR4, 32 GB eMMC 32 MB Shared Packet Buffer Memory	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration
Power supply	2 fieldreplaceable, hotswappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A and JL670A.	2 field-replaceable, hot-swappable power supply slots 1 minimum power supply required (ordered separately). Supported PSUs JL086A, JL087A, JL670A and JL758A.	2 fieldreplaceable, hotswappable power supply slots	2 fieldreplaceable, hotswappable power supply slots	2 fieldreplaceable, hotswappable power supply slots
PoE capability	Maximum PoE power: 2880W	Maximum PoE power: 2640W	Maximum PoE power: Up to 370W, 720W, 1440W, 2640W, or 2880W, depending on model and installed power supplies	Maximum PoE power: Up to 370W, 720W, 1440W, 2640W, or 2880W, depending on model and installed power supplies	Maximum PoE power: Up to 370W, 720W, 1440W, 2640W, or 2880W, depending on model and installed power supplies
Management features	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software				

	HPE Aruba Networking CX 6300M 48p Smart Rate 1G/2.5G/5G Class6 PoE 4p SFP56 50G TAA Switch (S0G04A)	HPE Aruba Networking CX 6300M 48p SR10 1G/2.5G/5G/10G PTP/AVB Class8 PoE and 4p 100G MACsec Switch (S0E91A)	HPE Networking CX6300M 16p 1G 8p Smart Rate 10G Class8 PoE 2p SFP56 50G 2p SFP28 25G Switch (S6X58A)	HPE Networking CX6300M 16p 1G 8p Smart Rate 10G Class8 PoE 2p SFP56 50G 2p SFP28 25G TAA Sw (S7K41A)	HPE Networking CX6300M 24p 1G Class8 PoE 2p SFP56 50G 2p SFP28 25G MACsec Switch (S6X60A)
Operating temperature	32°F to 113°F (0°C to 45°C) up to 5000 ft. Derate 1°C for every 1000 ft from 5000 ft to 10000 ft.	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].
Warranty	Limited lifetime warranty. See warranty details.				

	HPE Networking CX6300M 24p 1G Class8 PoE 2p SFP56 50G 2p SFP28 25G MACsec TAA Sw (S7K43A)	HPE Networking CX6300M 48p 1G Class8 PoE 2p SFP56 50G 2p SFP28 25G MACsec Switch (S6X59A)	HPE Networking CX6300M 48p 1G Class8 PoE 2p SFP56 50G 2p SFP28 25G MACsec TAA Sw (S7K42A)	HPE Networking CX6300M 48p Smart Rate 10G PTP/AVB 4p QSFP28 100G MACsec 4320W TAA Sw (SOE93A)	HPE Networking CX6300M 48p Smart Rate 10G PTP/AVB Class8 PoE 4320W 4p QSFP28 100G MACsec Sw (SOE92A)
Power consumption	Up to 211W depending on model				
Input voltage	Maximum 120V/208V–240V depending on PSU model				
Ports	24x 1G Copper ports	48x of 1G Copper ports	48x 1G Copper ports	Up to 48 HPE Smart Rate ports (1G/2.5G/5G/10GbE)	Up to 48 HPE Smart Rate ports (1G/2.5G/5G/10GbE)
Latency	Depending on model				
Switching capacity	From to 880 Gbps to 1760 Gbps, depending on model and configuration				
Stacking capabilities	Up to 10 members per stack. Note: CX 6300L switches only stack with other CX 6300L switches				
Throughput	From to 660 Mpps to 1310 Mpps, depending on model and configuration				
Memory and processor	CPU: Dual-core Arm® Cortex®-A9 @ 1.8GHz Memory: 8 GB DDR4, 32 GB eMMC Flash: 8 MB, 16 MB, or 32 MB, depending on model and configuration				
Power supply	2 fieldreplaceable, hotswappable power supply slots				
PoE capability	Maximum PoE power: Up to 370W, 720W, 1440W, 2640W, or 2880W, depending on model and installed power supplies				
Management features	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software				
Operating temperature	32°F to 113°F (0°C to 45°C) up to 5,000 ft. Derate 1°C for every 1,000 ft from 50,00 ft to 10,000 ft. Can support excursion to 131°F (55°C) for short periods of time [3].				
Warranty	Limited lifetime warranty. See warranty details.				

Related Options

The following options are available for these series:

SKU	Description
-----	-------------

Adapters

S1H23A	HPE Aruba Networking CX Switch Bluetooth Adapter
--------	--

Cables/Cable Kits

S1J07A	HPE Aruba Networking 50G QSFP56 to SFP56 0.65m DAC Cable
S1J08A	HPE Aruba Networking 50G QSFP56 to SFP56 3m DAC Cable
R9J32A	HPE Aruba Networking USB-A reversible to USB-C PC-to-Switch 3m Cable
R9J33A	HPE Aruba Networking USB-C to USB-C PC-to-Switch 3m Cable
R9G48B	HPE Aruba Networking USB-A-RJ45 PC-to-Switch PIN6TX-3RX 2.5m Cable
R8Z87A	HPE Aruba Networking USB-A-RJ45 PIN3TX-6RX 2.5m Cable

Converters

845970-B21	HPE QSFP28 to SFP28 Adapter
------------	-----------------------------

Fans/Fan Options

R9F62A	HPE Aruba Networking CX 6300M Power-to-Port Airflow Fan Tray
JL761A	HPE Aruba Networking CX 6300M Power-to-Port Fan Tray
JL714A	HPE Aruba Networking X741 Port-to-Power Fan
JL669B	HPE Aruba Networking X751 Front to Back Fan Tray

HPE Aruba Networking Software

R9G36AAE	HPE Aruba Networking NetEdit Single Node 1-year Subscription E-STU
JL639AAE	HPE Aruba Networking NetEdit Single Node 1yr Subscription E-STU
R9G37AAE	HPE Aruba Networking NetEdit Single Node 3-year Subscription E-STU
JL640AAE	HPE Aruba Networking NetEdit Single Node 3yr Subscription E-STU

Mounting Rack/Rail Options

R9F57A	HPE Aruba Networking 1U Universal 4-post Rack Mount Kit
R9F60A	HPE Aruba Networking Universal 4-post Duct Kit
J9583B	HPE Aruba Networking X414 1U Universal 4-post Rack Mount Kit
JL716A	HPE Aruba Networking X544 Universal 4-post Duct Kit (Must order 4-post rack mount kit)

Networking Software

R8D18AAE	HPE Aruba Networking Fabric Composer Device Management Service Tier 3 Switch 1y Subscription E-STU
----------	--

R9G31AAE	HPE Aruba Networking Fabric Composer Device Management Service Tier 3 Switch 1y Subscription E-STU
R9G32AAE	HPE Aruba Networking Fabric Composer Device Management Service Tier 3 Switch 3y Subscription E-STU
R8D19AAE	HPE Aruba Networking Fabric Composer Device Management Service Tier 3 Switch 3y Subscription E-STU
R9G33AAE	HPE Aruba Networking Fabric Composer Device Management Service Tier 3 Switch 5y Subscription E-STU
R8D20AAE	HPE Aruba Networking Fabric Composer Device Management Service Tier 3 Switch 5y Subscription E-STU

Power Management Options

R9F61A	HPE Aruba Networking CX 6300M 12VDC 250W 100-240VAC Power-to-Port Airflow Power Supply Unit
JL757A	HPE Aruba Networking CX 6300M 250W 36-72VDC Input Non-PoE Power Supply
JL758A	HPE Aruba Networking CX 6300M 1050W 36-72VDC Input PoE Power Supply
JL085A	HPE Aruba Networking X371 12VDC 250W 100-240VAC Power Supply
JL760A	HPE Aruba Networking X371 12VDC 250W 100-240VAC Power-to-Port Power Supply
JL086A	HPE Aruba Networking X372 54VDC 680W 100-240VAC Power Supply
JL087A	HPE Aruba Networking X372 54VDC 1050W 110-240VAC Power Supply
JL670A	HPE Aruba Networking X372 54VDC 1600W 110-240VAC Power Supply

Private and Hybrid Cloud

R6V03AAE	HPE Aruba Networking Central On-Premises Switch Class3 Advanced 1-year Subscription E-STU
R6V04AAE	HPE Aruba Networking Central On-Premises Switch Class3 Advanced 3-year Subscription E-STU
R6V05AAE	HPE Aruba Networking Central On-Premises Switch Class3 Advanced 5-year Subscription E-STU
R6V06AAE	HPE Aruba Networking Central On-Premises Switch Class3 Advanced 7-year Subscription E-STU
R6V07AAE	HPE Aruba Networking Central On-Premises Switch Class3 Advanced 10-year Subscription E-STU
R3K02AAE	HPE Aruba Networking Central Switch Class3 Foundation 10-year Subscription E-STU
Q9Y78AAE	HPE Aruba Networking Central Switch Class-3 Foundation 1 year Subscription E-STU
Q9Y79AAE	HPE Aruba Networking Central Switch Class-3 Foundation 3 year Subscription E-STU
Q9Y80AAE	HPE Aruba Networking Central Switch Class-3 Foundation 5 year Subscription E-STU
Q9Y81AAE	HPE Aruba Networking Central Switch Class-3 Foundation 7 year Subscription E-STU
R6U83AAE	HPE Aruba Networking Central on Prem Switch Class-3 Foundation 1 year Subscription E-STU
R6U84AAE	HPE Aruba Networking Central on Prem Switch Class-3 Foundation 3 year Subscription E-STU
R6U85AAE	HPE Aruba Networking Central on Prem Switch Class-3 Foundation 5 year Subscription E-STU
R6U86AAE	HPE Aruba Networking Central on Prem Switch Class-3 Foundation 7 year Subscription E-STU
R6U87AAE	HPE Aruba Networking Central on Prem Switch Class-3 Foundation 10 year Subscription E-STU

Transceiver Options

J4860D	HPE Aruba Networking 1G SFP LC LH 70km SMF Transceiver
JL746A	HPE Aruba Networking 1G SFP LC LX 10km SMF TAA Transceiver

R9Q44A	HPE Aruba Networking 1G SFP LC LX 10km SMF TAA Transceiver
J4859D	HPE Aruba Networking 1G SFP LC LX 10km SMF Transceiver
JL745A	HPE Aruba Networking 1G SFP LC SX 500m MMF TAA Transceiver
R9Q43A	HPE Aruba Networking 1G SFP LC SX 500m MMF TAA Transceiver
J4858D	HPE Aruba Networking 1G SFP LC SX 500m OM2 MMF Transceiver
R9F86A	HPE Aruba Networking 1G SFP LC SX 500m OM2 MMF Transceiver
JL747B	HPE Aruba Networking 1G SFP RJ45 100m Cat5e TAA Transceiver
J8177E	HPE Aruba Networking 1G SFP RJ45 100m Cat5e Transceiver
JL747A	HPE Aruba Networking 1G SFP RJ45 T 100m Cat5e TAA Transceiver
R9Q45A	HPE Aruba Networking 1G SFP RJ45 T 100m Cat5e TAA Transceiver
R9F87A	HPE Aruba Networking 1G SFP RJ45 T 100m Cat5e Transceiver
S2P32A	HPE Aruba Networking 10G ER SFP+ LC 40km SMF C-Class Transceiver
S2P31A	HPE Aruba Networking 10G LR SFP+ LC 10km SMF C-Class Transceiver
J9153D	HPE Aruba Networking 10G SFP+ LC ER 40km SMF Transceiver
JL749A	HPE Aruba Networking 10G SFP+ LC LR 10km SMF TAA Transceiver
R9Q47A	HPE Aruba Networking 10G SFP+ LC LR 10km SMF TAA Transceiver
J9151E	HPE Aruba Networking 10G SFP+ LC LR 10km SMF Transceiver
J9152D	HPE Aruba Networking 10G SFP+ LC LRM 220m OM2 MMF Transceiver
JL748A	HPE Aruba Networking 10G SFP+ LC SR 300m MMF TAA Transceiver
R9Q46A	HPE Aruba Networking 10G SFP+ LC SR 300m MMF TAA Transceiver
J9150D	HPE Aruba Networking 10G SFP+ LC SR 300m OM3 MMF Transceiver
R9F82A	HPE Aruba Networking 10G SFP+ LC SR 300m OM3 MMF Transceiver
J9281D	HPE Aruba Networking 10G SFP+ to SFP+ 1m Direct Attach Copper Cable
R9F83A	HPE Aruba Networking 10G SFP+ to SFP+ 1m Direct Attach Copper Cable
J9283D	HPE Aruba Networking 10G SFP+ to SFP+ 3m Direct Attach Copper Cable
R9F84A	HPE Aruba Networking 10G SFP+ to SFP+ 3m Direct Attach Copper Cable
R9X54A	HPE Aruba Networking 10G SMF Simplex LC BiDi 40km-Downstream 1330/1270 Transceiver
R9X55A	HPE Aruba Networking 10G SMF Simplex LC BiDi 40km-Upstream 1270/1330 Transceiver
S2P30A	HPE Aruba Networking 10G SR SFP+ LC 400m OM4 MMF C-Class Transceiver
R9F85A	HPE Aruba Networking 10GBASE-T SFP+ RJ45 30m Cat6A Transceiver
JL563C	HPE Aruba Networking 10GBASE-T SFP+ RJ45 30m Cat6A Transceiver
S1C96A	HPE Aruba Networking 25G BiDi 10km-Downstream 1330/1270 Transceiver
S1C98A	HPE Aruba Networking 25G BiDi 10km-Upstream 1270/1330 Transceiver
SOV70A	HPE Aruba Networking 25G BiDi 40km-Downstream 1314/1289 Transceiver
SOV71A	HPE Aruba Networking 25G BiDi 40km-Upstream 1289/1314 Transceiver
SOV69A	HPE Aruba Networking 25G ER LC 40km SMF Transceiver

S2P34A	HPE Aruba Networking 25G LR SFP28 LC 10km SMF C-Class Transceiver
S2N63A	HPE Aruba Networking 25G LR SFP28 LC 10km SMF TAA Transceiver
JL486A	HPE Aruba Networking 25G SFP28 LC LR 10km SMF Transceiver
R9F89A	HPE Aruba Networking 25G SFP28 LC SR 100m MMF Transceiver
JL484A	HPE Aruba Networking 25G SFP28 LC SR 100m MMF Transceiver
JL485A	HPE Aruba Networking 25G SFP28 LC eSR 400m MMF Transceiver
R9F90A	HPE Aruba Networking 25G SFP28 LC eSR 400m MMF Transceiver
JL487A	HPE Aruba Networking 25G SFP28 to SFP28 0.65m Direct Attach Cable
R9F91A	HPE Aruba Networking 25G SFP28 to SFP28 0.65m Direct Attach Copper Cable
ROM44A	HPE Aruba Networking 25G SFP28 to SFP28 3m Active Optical Cable
JL488A	HPE Aruba Networking 25G SFP28 to SFP28 3m Direct Attach Copper Cable
R9F92A	HPE Aruba Networking 25G SFP28 to SFP28 3m Direct Attach Copper Cable
JL489A	HPE Aruba Networking 25G SFP28 to SFP28 5m Direct Attach Copper Cable
R9F93A	HPE Aruba Networking 25G SFP28 to SFP28 5m Direct Attach Copper Cable
ROM45A	HPE Aruba Networking 25G SFP28 to SFP28 7m Active Optical Cable
ROZ21A	HPE Aruba Networking 25G SFP28 to SFP28 15m Active Optical Cable
S2P33A	HPE Aruba Networking 25G SR SFP28 LC 100m MMF C-Class Transceiver
S5U19A	HPE Aruba Networking 25G eSR SFP28 LC 400m MMF TAA Transceiver
JL308A	HPE Aruba Networking 40G QSFP+ LC Bidirectional 150m MMF 2-strand Transceiver
Q9G82A	HPE Aruba Networking 40G QSFP+ LC ER4 40km SMF Transceiver
ROZ22A	HPE Aruba Networking 40G QSFP+ to QSFP+ 7m Active Optical Cable
ROZ23A	HPE Aruba Networking 40G QSFP+ to QSFP+ 15m Active Optical Cable
ROZ24A	HPE Aruba Networking 40G QSFP+ to QSFP+ 30m Active Optical Cable
S1C92A	HPE Aruba Networking 50G BiDi 10km-Downstream 1330/1270 Transceiver
S1C94A	HPE Aruba Networking 50G BiDi 10km-Upstream 1270/1330 Transceiver
SOV66A	HPE Aruba Networking 50G ER 40km SMF Transceiver
SOV65A	HPE Aruba Networking 50G LR 10km SMF Transceiver
ROM48A	HPE Aruba Networking 50G SFP56 LC SR 100m MMF Transceiver
R9G06A	HPE Aruba Networking 50G SFP56 to SFP56 0.65m Direct Attach Copper Cable
ROM46A	HPE Aruba Networking 50G SFP56 to SFP56 0.65m Direct Attach Copper Cable
ROM47A	HPE Aruba Networking 50G SFP56 to SFP56 3m Direct Attach Copper Cable
R9G07A	HPE Aruba Networking 50G SFP56 to SFP56 3m Direct Attach Copper Cable
SOV64A	HPE Aruba Networking 50G eSR 300m MMF Transceiver
ROZ30A	HPE Aruba Networking 100G QSFP28 LC CWDM4 2km SMF Transceiver
JL743A	HPE Aruba Networking 100G QSFP28 LC ER4L 40km SMF Transceiver
R9B63A	HPE Aruba Networking 100G QSFP28 LC FR1 SMF 2km Transceiver

JL310A	HPE Aruba Networking 100G QSFP28 LC LR4 10km SMF 2-strand Transceiver
JL309A	HPE Aruba Networking 100G QSFP28 MPO SR4 100m 12-fiber MPO OM3 MMF Transceiver
ROZ25A	HPE Aruba Networking 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable
JL856A	HPE Aruba Networking 100G QSFP28 to QSFP28 2m Active Optical Cable
JL307A	HPE Aruba Networking 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable
ROZ26A	HPE Aruba Networking 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable
ROZ27A	HPE Aruba Networking 100G QSFP28 to QSFP28 7m Active Optical Cable
ROZ28A	HPE Aruba Networking 100G QSFP28 to QSFP28 15m Active Optical Cable
ROZ29A	HPE Aruba Networking 100G QSFP28 to QSFP28 30m Active Optical Cable
S4B44A	HPE Aruba Networking 100G SR1.2 QSFP28 LC 100m MMF Transceiver
S1C93A	HPE Aruba Networking 100G SR2 MPO QSFP28 100m MMF Transceiver
R9F88A	HPE Aruba Networking 100M SFP LC FX 2km MMF Transceiver
J9054D	HPE Aruba Networking 100M SFP LC FX 2km MMF Transceiver
JH232A	HPE Networking X142 40G QSFP+ LC LR4 SM Transceiver
JH231A	HPE Networking X142 40G QSFP+ MPO SR4 Transceiver
JH233A	HPE Networking X142 40G QSFP+ MPO eSR4 300M Transceiver
JH234A	HPE Networking X242 40G QSFP+ to QSFP+ 1m Direct Attach Copper Cable
JH235A	HPE Networking X242 40G QSFP+ to QSFP+ 3m Direct Attach Copper Cable
JH236A	HPE Networking X242 40G QSFP+ to QSFP+ 5m Direct Attach Copper Cable

Related Services

The following services are available for these series:

SKU	Description
Technology Services	
H89N9E	HPE Aruba Networking 1 Year Foundational Care 4-Hour Exchange 6300M 48 DCN Service
H00TNE	HPE Aruba Networking 1 Year Foundational Care 4-Hour Exchange 6300M 48p SR10 Service
H00GBE	HPE Aruba Networking 1 Year Foundational Care 4-Hour Exchange Volume T1 6300M 48 DCN Service
H00XPE	HPE Aruba Networking 1 Year Foundational Care 4-Hour Exchange Volume T1 6300M 48p SR10 Service
H00GCE	HPE Aruba Networking 1 Year Foundational Care 4-Hour Exchange Volume T2 6300M 48 DCN Service
H00XQE	HPE Aruba Networking 1 Year Foundational Care 4-Hour Exchange Volume T2 6300M 48p SR10 Service
H89P3E	HPE Aruba Networking 1 Year Foundational Care 4-Hour Onsite 6300M 48 DCN Service
H00TSE	HPE Aruba Networking 1 Year Foundational Care 4-Hour Onsite 6300M 48p SR10 Service

H89P2E	HPE Aruba Networking 1 Year Foundational Care 4-Hour Onsite Hardware Only 6300M 48 DCN Service
H00TRE	HPE Aruba Networking 1 Year Foundational Care 4-Hour Onsite Hardware Only 6300M 48p SR10 Service
H00GHE	HPE Aruba Networking 1 Year Foundational Care 24x7 Technical Supp Volume Tier 26300M 48 DCN Service
H00XVE	HPE Aruba Networking 1 Year Foundational Care 24x7 Technical Supp Volume Tier 26300M 48p SR10 SVC
H89P5E	HPE Aruba Networking 1 Year Foundational Care 24x7 Technical Support 6300M 48 DCN Service
H00TVE	HPE Aruba Networking 1 Year Foundational Care 24x7 Technical Support 6300M 48p SR10 Service
H89P4E	HPE Aruba Networking 1 Year Foundational Care 24x7 with CDMR 6300M 48 DCN Service
H00TTE	HPE Aruba Networking 1 Year Foundational Care 24x7 with CDMR 6300M 48p SR10 Service
H89P6E	HPE Aruba Networking 1 Year Foundational Care Call-To-Repair 6300M 48 DCN Service
H00TWE	HPE Aruba Networking 1 Year Foundational Care Call-To-Repair 6300M 48p SR10 Service
H89P7E	HPE Aruba Networking 1 Year Foundational Care Call-To-Repair with CDMR 6300M 48 DCN Service
H00TXE	HPE Aruba Networking 1 Year Foundational Care Call-To-Repair with CDMR 6300M 48p SR10 Service
H89P0E	HPE Aruba Networking 1 Year Foundational Care Next Business Day 6300M 48 DCN Service
H00TPE	HPE Aruba Networking 1 Year Foundational Care Next Business Day 6300M 48p SR10 Service
H89N7E	HPE Aruba Networking 1 Year Foundational Care Next Business Day Exchange 6300M 48 DCN Service
H00TLE	HPE Aruba Networking 1 Year Foundational Care Next Business Day Exchange 6300M 48p SR10 Service
H89N8E	HPE Aruba Networking 1 Year Foundational Care Next Business Day Exchange HW Only 6300M 48 DCN SVC
H00TME	HPE Aruba Networking 1 Year Foundational Care Next Business Day Exchange HardwareOnly6300M48pSR10SVC
H00XKE	HPE Aruba Networking 1 Year Foundational Care Next Business Day Exchange Vol T1 6300M 48p SR10 SVC
H00XLE	HPE Aruba Networking 1 Year Foundational Care Next Business Day Exchange Vol T2 6300M 48p SR10 SVC
H00FWE	HPE Aruba Networking 1 Year Foundational Care Next Business Day Exchange Volume T1 6300M 48 DCN SVC
H00FXE	HPE Aruba Networking 1 Year Foundational Care Next Business Day Exchange Volume T2 6300M 48 DCN SVC
H89P1E	HPE Aruba Networking 1 Year Foundational Care Next Business Day with CDMR 6300M 48 DCN Service
H00TQE	HPE Aruba Networking 1 Year Foundational Care Next Business Day with CDMR 6300M 48p SR10 Service
H63C0E	HPE Aruba Networking 1Y 24x7 Technical Support 6300M 24SR PoE SVC
H64E2E	HPE Aruba Networking 1Y 24x7 Technical Support 6300M 24p SFP+ LRM SVC
H63R1E	HPE Aruba Networking 1Y 24x7 Technical Support 6300M 48p SR5 PoE SVC
H63J3E	HPE Aruba Networking 1Y 24x7 Technical Support Volume Tier 26300M 24SR PoE SVC
H64L5E	HPE Aruba Networking 1Y 24x7 Technical Support Volume Tier 26300M 24p SFP+ LRM SVC
H63X4E	HPE Aruba Networking 1Y 24x7 Technical Support Volume Tier 26300M 48p SR5 PoE SVC
HR6D4E	HPE Aruba Networking 1Y Software+Technical Support 6300F 24 PoE Switch SVC

HR6W4E	HPE Aruba Networking 1Y Software+Technical Support 6300F 24 Switch SVC
HR5U9E	HPE Aruba Networking 1Y Software+Technical Support 6300F 48 PoE Switch SVC
HR6M9E	HPE Aruba Networking 1Y Software+Technical Support 6300F 48 Switch SVC
HR5H2E	HPE Aruba Networking 1Y Software+Technical Support 6300M 24 PoE Switch SVC
HL5X9E	HPE Aruba Networking 1Y Software+Technical Support 6300M 24 SR PoE Switch SVC
HL7H2E	HPE Aruba Networking 1Y Software+Technical Support 6300M 24 Switch SVC
HR4B8E	HPE Aruba Networking 1Y Software+Technical Support 6300M 24SFP Switch SVC
HL6L3E	HPE Aruba Networking 1Y Software+Technical Support 6300M 48 PoE Switch SVC
HR4Q2E	HPE Aruba Networking 1Y Software+Technical Support 6300M 48 SR PoE Switch SVC
HR5M1E	HPE Aruba Networking 1Y Software+Technical Support 6300M 48 Switch SVC
H58Z6E	HPE Aruba Networking 1Y Software+Technical Support 6300M 48 Switch SVC
HR6K7E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6300F 24 PoE Switch SVC
HR7C7E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6300F 24 Switch SVC
HR6B2E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6300F 48 PoE Switch SVC
HL8F8E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6300F 48 Switch SVC
HL6W5E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6300M 24 PoE Switch SVC
HR4N0E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6300M 24 SR PoE Switch SVC
HL7P5E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6300M 24 Switch SVC
HL5V7E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6300M 24SFP Switch SVC
HL6N0E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6300M 48 PoE Switch SVC
HR4W5E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6300M 48 SR PoE Switch SVC
HR5N8E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6300M 48 Switch SVC
H59B3E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6300M 48 Switch SVC
H89Q0E	HPE Aruba Networking 3 Year Foundational Care 4-Hour Exchange 6300M 48 DCN Service
H00VBE	HPE Aruba Networking 3 Year Foundational Care 4-Hour Exchange 6300M 48p SR10 Service
H00GSE	HPE Aruba Networking 3 Year Foundational Care 4-Hour Exchange Volume T1 6300M 48 DCN Service
H00YGE	HPE Aruba Networking 3 Year Foundational Care 4-Hour Exchange Volume T1 6300M 48p SR10 Service
H00GTE	HPE Aruba Networking 3 Year Foundational Care 4-Hour Exchange Volume T2 6300M 48 DCN Service
H00YHE	HPE Aruba Networking 3 Year Foundational Care 4-Hour Exchange Volume T2 6300M 48p SR10 Service
H89Q6E	HPE Aruba Networking 3 Year Foundational Care 4-Hour Onsite 6300M 48 DCN Service
H00VJE	HPE Aruba Networking 3 Year Foundational Care 4-Hour Onsite 6300M 48p SR10 Service
H89Q5E	HPE Aruba Networking 3 Year Foundational Care 4-Hour Onsite Hardware Only 6300M 48 DCN Service
H00VHE	HPE Aruba Networking 3 Year Foundational Care 4-Hour Onsite Hardware Only 6300M 48p SR10 Service
H00GZE	HPE Aruba Networking 3 Year Foundational Care 24x7 Technical Supp Volume Tier 26300M 48 DCN Service

H00YNE	HPE Aruba Networking 3 Year Foundational Care 24x7 Technical Supp Volume Tier 26300M 48p SR10 SVC
H89Q8E	HPE Aruba Networking 3 Year Foundational Care 24x7 Technical Support 6300M 48 DCN Service
H00VLE	HPE Aruba Networking 3 Year Foundational Care 24x7 Technical Support 6300M 48p SR10 Service
H89Q7E	HPE Aruba Networking 3 Year Foundational Care 24x7 with CDMR 6300M 48 DCN Service
H00VKE	HPE Aruba Networking 3 Year Foundational Care 24x7 with CDMR 6300M 48p SR10 Service
H89Q9E	HPE Aruba Networking 3 Year Foundational Care Call-To-Repair 6300M 48 DCN Service
H00VME	HPE Aruba Networking 3 Year Foundational Care Call-To-Repair 6300M 48p SR10 Service
H89R0E	HPE Aruba Networking 3 Year Foundational Care Call-To-Repair with CDMR 6300M 48 DCN Service
H00VNE	HPE Aruba Networking 3 Year Foundational Care Call-To-Repair with CDMR 6300M 48p SR10 Service
H89Q1E	HPE Aruba Networking 3 Year Foundational Care Next Business Day 6300M 48 DCN Service
H00VCE	HPE Aruba Networking 3 Year Foundational Care Next Business Day 6300M 48p SR10 Service
H89P9E	HPE Aruba Networking 3 Year Foundational Care Next Business Day Exchange 6300M 48 DCN Service
H00TZE	HPE Aruba Networking 3 Year Foundational Care Next Business Day Exchange 6300M 48p SR10 Service
H89P8E	HPE Aruba Networking 3 Year Foundational Care Next Business Day Exchange HW Only 6300M 48 DCN SVC
H00TYE	HPE Aruba Networking 3 Year Foundational Care Next Business Day Exchange HardwareOnly6300M48pSR10SVC
H00YBE	HPE Aruba Networking 3 Year Foundational Care Next Business Day Exchange Vol T1 6300M 48p SR10 SVC
H00YCE	HPE Aruba Networking 3 Year Foundational Care Next Business Day Exchange Vol T2 6300M 48p SR10 SVC
H00GNE	HPE Aruba Networking 3 Year Foundational Care Next Business Day Exchange Volume T1 6300M 48 DCN SVC
H00GPE	HPE Aruba Networking 3 Year Foundational Care Next Business Day Exchange Volume T2 6300M 48 DCN SVC
H89Q2E	HPE Aruba Networking 3 Year Foundational Care Next Business Day with CDMR 6300M 48 DCN Service
H00VDE	HPE Aruba Networking 3 Year Foundational Care Next Business Day with CDMR 6300M 48p SR10 Service
H63D3E	HPE Aruba Networking 3Y 24x7 Technical Support 6300M 24SR PoE SVC
H64F5E	HPE Aruba Networking 3Y 24x7 Technical Support 6300M 24p SFP+ LRM SVC
H63S4E	HPE Aruba Networking 3Y 24x7 Technical Support 6300M 48p SR5 PoE SVC
H63K8E	HPE Aruba Networking 3Y 24x7 Technical Support Volume Tier 26300M 24SR PoE SVC
H64N0E	HPE Aruba Networking 3Y 24x7 Technical Support Volume Tier 26300M 24p SFP+ LRM SVC
H63Y9E	HPE Aruba Networking 3Y 24x7 Technical Support Volume Tier 26300M 48p SR5 PoE SVC
HR6E7E	HPE Aruba Networking 3Y Software+Technical Support 6300F 24 PoE Switch SVC
HR6X7E	HPE Aruba Networking 3Y Software+Technical Support 6300F 24 Switch SVC
HR5W2E	HPE Aruba Networking 3Y Software+Technical Support 6300F 48 PoE Switch SVC
HR6P2E	HPE Aruba Networking 3Y Software+Technical Support 6300F 48 Switch SVC
HL6R5E	HPE Aruba Networking 3Y Software+Technical Support 6300M 24 PoE Switch SVC

HL5Z2E	HPE Aruba Networking 3Y Software+Technical Support 6300M 24 SR PoE Switch SVC
HL7J5E	HPE Aruba Networking 3Y Software+Technical Support 6300M 24 Switch SVC
HR4D1E	HPE Aruba Networking 3Y Software+Technical Support 6300M 24SFP Switch SVC
HR5A0E	HPE Aruba Networking 3Y Software+Technical Support 6300M 48 PoE Switch SVC
HR4R5E	HPE Aruba Networking 3Y Software+Technical Support 6300M 48 SR PoE Switch SVC
HR5N4E	HPE Aruba Networking 3Y Software+Technical Support 6300M 48 Switch SVC
H59A9E	HPE Aruba Networking 3Y Software+Technical Support 6300M 48 Switch SVC
HR6M2E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6300F 24 PoE Switch SVC
HR7E2E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6300F 24 Switch SVC
HL7U9E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6300F 48 PoE Switch SVC
HL8H3E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6300F 48 Switch SVC
HL6Y0E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6300M 24 PoE Switch SVC
HR4P5E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6300M 24 SR PoE Switch SVC
HL7R0E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6300M 24 Switch SVC
HR4F0E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6300M 24SFP Switch SVC
HL6P5E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6300M 48 PoE Switch SVC
HR4Y0E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6300M 48 SR PoE Switch SVC
H59C8E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6300M 48 Switch SVC
HR5Q3E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6300M 48 Switch SVC
H58T8E	HPE Aruba Networking 4Y Software+Technical Support 6300M 48 Switch SVC
H59E3E	HPE Aruba Networking 4Y Software+Technical Support Vol T2 6300M 48 Switch SVC
H89S6E	HPE Aruba Networking 5 Year Foundational Care 4-Hour Exchange 6300M 48 DCN Service
H00WHE	HPE Aruba Networking 5 Year Foundational Care 4-Hour Exchange 6300M 48p SR10 Service
H00JDE	HPE Aruba Networking 5 Year Foundational Care 4-Hour Exchange Volume T1 6300M 48 DCN Service
H00ZRE	HPE Aruba Networking 5 Year Foundational Care 4-Hour Exchange Volume T1 6300M 48p SR10 Service
H00JFE	HPE Aruba Networking 5 Year Foundational Care 4-Hour Exchange Volume T2 6300M 48 DCN Service
H00ZSE	HPE Aruba Networking 5 Year Foundational Care 4-Hour Exchange Volume T2 6300M 48p SR10 Service
H89T2E	HPE Aruba Networking 5 Year Foundational Care 4-Hour Onsite 6300M 48 DCN Service
H00WPE	HPE Aruba Networking 5 Year Foundational Care 4-Hour Onsite 6300M 48p SR10 Service
H89T1E	HPE Aruba Networking 5 Year Foundational Care 4-Hour Onsite Hardware Only 6300M 48 DCN Service
H00WNE	HPE Aruba Networking 5 Year Foundational Care 4-Hour Onsite Hardware Only 6300M 48p SR10 Service
H00JLE	HPE Aruba Networking 5 Year Foundational Care 24x7 Technical Supp Volume Tier 26300M 48 DCN Service
H00ZYE	HPE Aruba Networking 5 Year Foundational Care 24x7 Technical Supp Volume Tier 26300M 48p SR10 SVC

H89T4E	HPE Aruba Networking 5 Year Foundational Care 24x7 Technical Support 6300M 48 DCN Service
H00WRE	HPE Aruba Networking 5 Year Foundational Care 24x7 Technical Support 6300M 48p SR10 Service
H89T3E	HPE Aruba Networking 5 Year Foundational Care 24x7 with CDMR 6300M 48 DCN Service
H00WQE	HPE Aruba Networking 5 Year Foundational Care 24x7 with CDMR 6300M 48p SR10 Service
H89T5E	HPE Aruba Networking 5 Year Foundational Care Call-To-Repair 6300M 48 DCN Service
H00WSE	HPE Aruba Networking 5 Year Foundational Care Call-To-Repair 6300M 48p SR10 Service
H89T6E	HPE Aruba Networking 5 Year Foundational Care Call-To-Repair with CDMR 6300M 48 DCN Service
H00WTE	HPE Aruba Networking 5 Year Foundational Care Call-To-Repair with CDMR 6300M 48p SR10 Service
H89S7E	HPE Aruba Networking 5 Year Foundational Care Next Business Day 6300M 48 DCN Service
H00WJE	HPE Aruba Networking 5 Year Foundational Care Next Business Day 6300M 48p SR10 Service
H89S5E	HPE Aruba Networking 5 Year Foundational Care Next Business Day Exchange 6300M 48 DCN Service
H00WGE	HPE Aruba Networking 5 Year Foundational Care Next Business Day Exchange 6300M 48p SR10 Service
H89S4E	HPE Aruba Networking 5 Year Foundational Care Next Business Day Exchange HW Only 6300M 48 DCN SVC
H00WFE	HPE Aruba Networking 5 Year Foundational Care Next Business Day Exchange HardwareOnly6300M48pSR10SVC
H00ZME	HPE Aruba Networking 5 Year Foundational Care Next Business Day Exchange Vol T1 6300M 48p SR10 SVC
H00ZNE	HPE Aruba Networking 5 Year Foundational Care Next Business Day Exchange Vol T2 6300M 48p SR10 SVC
H00HYE	HPE Aruba Networking 5 Year Foundational Care Next Business Day Exchange Volume T1 6300M 48 DCN SVC
H00HZE	HPE Aruba Networking 5 Year Foundational Care Next Business Day Exchange Volume T2 6300M 48 DCN SVC
H89S8E	HPE Aruba Networking 5 Year Foundational Care Next Business Day with CDMR 6300M 48 DCN Service
H00WKE	HPE Aruba Networking 5 Year Foundational Care Next Business Day with CDMR 6300M 48p SR10 Service
H63F9E	HPE Aruba Networking 5Y 24x7 Technical Support 6300M 24SR PoE SVC
H64J1E	HPE Aruba Networking 5Y 24x7 Technical Support 6300M 24p SFP+ LRM SVC
H63V0E	HPE Aruba Networking 5Y 24x7 Technical Support 6300M 48p SR5 PoE SVC
H63N8E	HPE Aruba Networking 5Y 24x7 Technical Support Volume Tier 26300M 24SR PoE SVC
H64R0E	HPE Aruba Networking 5Y 24x7 Technical Support Volume Tier 26300M 24p SFP+ LRM SVC
H64B9E	HPE Aruba Networking 5Y 24x7 Technical Support Volume Tier 26300M 48p SR5 PoE SVC
HR6H3E	HPE Aruba Networking 5Y Software+Technical Support 6300F 24 PoE Switch SVC
HR7A3E	HPE Aruba Networking 5Y Software+Technical Support 6300F 24 Switch SVC
HR5Y8E	HPE Aruba Networking 5Y Software+Technical Support 6300F 48 PoE Switch SVC
HR6R8E	HPE Aruba Networking 5Y Software+Technical Support 6300F 48 Switch SVC
HL6U1E	HPE Aruba Networking 5Y Software+Technical Support 6300M 24 PoE Switch SVC
HR4K6E	HPE Aruba Networking 5Y Software+Technical Support 6300M 24 SR PoE Switch SVC

HL7M1E	HPE Aruba Networking 5Y Software+Technical Support 6300M 24 Switch SVC
HL5T3E	HPE Aruba Networking 5Y Software+Technical Support 6300M 24SFP Switch SVC
HR5C6E	HPE Aruba Networking 5Y Software+Technical Support 6300M 48 PoE Switch SVC
HR4U1E	HPE Aruba Networking 5Y Software+Technical Support 6300M 48 SR PoE Switch SVC
HL7C6E	HPE Aruba Networking 5Y Software+Technical Support 6300M 48 Switch SVC
H58V1E	HPE Aruba Networking 5Y Software+Technical Support 6300M 48 Switch SVC
HL8B8E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6300F 24 PoE Switch SVC
HL8K6E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6300F 24 Switch SVC
HL7X9E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6300F 48 PoE Switch SVC
HR6U1E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6300F 48 Switch SVC
HR5J8E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6300M 24 PoE Switch SVC
HL6E1E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6300M 24 SR PoE Switch SVC
HL7U0E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6300M 24 Switch SVC
HR4J0E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6300M 24SFP Switch SVC
HR5E9E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6300M 48 PoE Switch SVC
HL6J0E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6300M 48 SR PoE Switch SVC
H58X4E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6300M 48 Switch SVC
HL7E9E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6300M 48 Switch SVC
H8XE6E	HPE Aruba Networking 6xxx and 8xxx Install Chassis Switch SVC
H01FCE	HPE Aruba Networking Foundational Care 1Y 4-Hour Exch 6300L 24 SW SVC
H01MJE	HPE Aruba Networking Foundational Care 1Y 4-Hour Exch 6300L 48 SW SVC
H01JDE	HPE Aruba Networking Foundational Care 1Y 4-Hour Exch Vol T1 6300L 24 SW SVC
H01QKE	HPE Aruba Networking Foundational Care 1Y 4-Hour Exch Vol T1 6300L 48 SW SVC
H01JFE	HPE Aruba Networking Foundational Care 1Y 4-Hour Exch Vol T2 6300L 24 SW SVC
H01QLE	HPE Aruba Networking Foundational Care 1Y 4-Hour Exch Vol T2 6300L 48 SW SVC
H01FHE	HPE Aruba Networking Foundational Care 1Y 4-Hour Onsite 6300L 24 SW SVC
H01MNE	HPE Aruba Networking Foundational Care 1Y 4-Hour Onsite 6300L 48 SW SVC
H01FGE	HPE Aruba Networking Foundational Care 1Y 4-Hour Onsite Hardware Only 6300L 24 SW SVC
H01MME	HPE Aruba Networking Foundational Care 1Y 4-Hour Onsite Hardware Only 6300L 48 SW SVC
HR6C8E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300F 24 PoE Switch SVC
HR6V8E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300F 24 Switch SVC
HR5U3E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300F 48 PoE Switch SVC
HL8D5E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300F 48 Switch SVC
H08MQE	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 16p CL8 Swch Service
HR5G6E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 24 PoE Switch SVC
H68D4E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 24 SR PoE Switch SVC

HL7G6E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 24 Switch SVC
HR4B2E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 24SFP Switch SVC
H63B4E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 24SR PoE SVC
H08RNE	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 24p 1G Fib Swch Service
H64D6E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 24p SFP+ LRM SVC
H08WME	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 32p CL8 Swch Service
HL6K7E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 48 PoE Switch SVC
HL6F8E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 48 SR PoE Switch SVC
H58Z1E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 48 Switch SVC
HR5L5E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 48 Switch SVC
H14GSE	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 48SR10 Swch Service
H14LME	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 48SR10 TAA Swch Service
H09BLE	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 48p 1G Fib Swch Service
H63Q5E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6300M 48p SR5 PoE SVC
HR6K2E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300F 24 PoE Switch SVC
HR7C2E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300F 24 Switch SVC
HR6A7E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300F 48 PoE Switch SVC
HL8F3E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300F 48 Switch SVC
H08PME	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 16p CL8 Swch Service
HL6W0E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 24 PoE Switch SVC
HR4M5E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 24 SR PoE Switch SVC
HL7P0E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 24 Switch SVC
HL5V2E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 24SFP Switch SVC
H63H8E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 24SR PoE SVC
H08TLE	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 24p 1G Fib Swch Service
H64L0E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 24p SFP+ LRM SVC
H08YKE	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 32p CL8 Swch Service
HL6M5E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 48 PoE Switch SVC
HR4W0E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 48 SR PoE Switch SVC
H58X0E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 48 Switch SVC
HL7E5E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 48 Switch SVC
H14JLE	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 48SR10 Swch Service
H14NGE	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 48SR10 TAA Swch Service
H09DJE	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 48p 1G Fib Swch Service
H63W9E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6300M 48p SR5 PoE SVC
HR6K3E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300F 24 PoE Switch SVC

HR7C3E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300F 24 Switch SVC
HR6A8E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300F 48 PoE Switch SVC
HL8F4E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300F 48 Switch SVC
H08PNE	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 16p CL8 Swch Service
HL6W1E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 24 PoE Switch SVC
HR4M6E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 24 SR PoE Switch SVC
HL7P1E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 24 Switch SVC
HL5V3E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 24SFP Switch SVC
H63H9E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 24SR PoE SVC
H08TME	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 24p 1G Fib Swch Service
H64L1E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 24p SFP+ LRM SVC
H08YLE	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 32p CL8 Swch Service
HL6M6E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 48 PoE Switch SVC
HR4W1E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 48 SR PoE Switch SVC
H58X1E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 48 Switch SVC
HL7E6E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 48 Switch SVC
H14JME	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 48SR10 Swch Service
H14NHE	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 48SR10 TAA Swch Service
H09DKE	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 48p 1G Fib Swch Service
H63X0E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6300M 48p SR5 PoE SVC
H08TSE	HPE Aruba Networking Foundational Care 1Y 4HR OS Technical Support V T2 6300M 24p 1GFib Swch Service
H09DQE	HPE Aruba Networking Foundational Care 1Y 4HR OS Technical Support V T2 6300M 48p 1GFib Swch Service
H08PTE	HPE Aruba Networking Foundational Care 1Y 4HR OS Technical Support Vol T2 6300M 16p CL8 Swch Service
H08YRE	HPE Aruba Networking Foundational Care 1Y 4HR OS Technical Support Vol T2 6300M 32p CL8 Swch Service
HR6D2E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300F 24 PoE Switch SVC
H68D8E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300F 24 Switch SVC
HR5U7E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300F 48 PoE Switch SVC
HR6M7E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300F 48 Switch SVC
H08MVE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 16p CL8 Swch Service
HR5H0E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 24 PoE Switch SVC
HL5X7E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 24 SR PoE Switch SVC
HL7H0E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 24 Switch SVC
HR4B6E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 24SFP Switch SVC
H63B8E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 24SR PoE SVC

H08RTE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 24p 1G Fib Swch Service
H64E0E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 24p SFP+ LRM SVC
H08WSE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 32p CL8 Swch Service
HL6L1E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 48 PoE Switch SVC
HR4Q0E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 48 SR PoE Switch SVC
HR5L9E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 48 Switch SVC
H58Z4E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 48 Switch SVC
H14GWE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 48SR10 Swch Service
H14LRE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 48SR10 TAA Swch Service
H09BRE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 48p 1G Fib Swch Service
H63Q9E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6300M 48p SR5 PoE SVC
HR6D3E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300F 24 PoE Switch SVC
HR6W3E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300F 24 Switch SVC
HR5U8E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300F 48 PoE Switch SVC
HR6M8E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300F 48 Switch SVC
H08MWE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300M 16p CL8 Swch Service
HR5H1E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300M 24 PoE Switch SVC
HL5X8E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300M 24 SR PoE Switch SVC
HL7H1E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300M 24 Switch SVC
HR4B7E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300M 24SFP Switch SVC
H08RVE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300M 24p 1G Fib Swch Service
H08WTE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300M 32p CL8 Swch Service
HL6L2E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300M 48 PoE Switch SVC
HR4Q1E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300M 48 SR PoE Switch SVC
HR5M0E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300M 48 Switch SVC
H58Z5E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300M 48 Switch SVC
H14GXE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300M 48SR10 Swch Service
H14LSE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300M 48SR10 TAA Swch Service
H09BSE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6300M 48p 1G Fib Swch Service
H08MTE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite HW Only 6300M 16p CL8 Swch Service
H08RSE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite HW Only 6300M 24p 1G Fib Swch Service
H08WRE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite HW Only 6300M 32p CL8 Swch Service
H09BQE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite HW Only 6300M 48p 1G Fib Swch Service
HR6D1E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300F 24 PoE Switch SVC
HR6W1E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300F 24 Switch SVC
HR5U6E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300F 48 PoE Switch SVC

H68D7E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300F 48 Switch SVC
HR5G9E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300M 24 PoE Switch SVC
HL5X6E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300M 24 SR PoE Switch SVC
HL7G9E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300M 24 Switch SVC
HR4B5E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300M 24SFP Switch SVC
H63B7E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300M 24SR PoE SVC
H64D9E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300M 24p SFP+ LRM SVC
HL6L0E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300M 48 PoE Switch SVC
HR4P9E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300M 48 SR PoE Switch SVC
HR5L8E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300M 48 Switch SVC
H58Z3E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300M 48 Switch SVC
H63Q8E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6300M 48p SR5 PoE SVC
H08MXE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Technical Support 6300M 16p CL8 Swch Service
H08RWE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Technical Support 6300M 24p 1G Fib Swch Service
H08WVE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Technical Support 6300M 32p CL8 Swch Service
H09BTE	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Technical Support 6300M 48p 1G Fib Swch Service
H63B9E	HPE Aruba Networking Foundational Care 1Y 24x7 CDMR 6300M 24SR PoE SVC
H64E1E	HPE Aruba Networking Foundational Care 1Y 24x7 CDMR 6300M 24p SFP+ LRM SVC
H63R0E	HPE Aruba Networking Foundational Care 1Y 24x7 CDMR 6300M 48p SR5 PoE SVC
H01FKE	HPE Aruba Networking Foundational Care 1Y 24x7 Technical Support 6300L 24 SW SVC
H01MQE	HPE Aruba Networking Foundational Care 1Y 24x7 Technical Support 6300L 48 SW SVC
H01JKE	HPE Aruba Networking Foundational Care 1Y 24x7 Technical Support Vol T 26300L 24 SW SVC
H01QQE	HPE Aruba Networking Foundational Care 1Y 24x7 Technical Support Vol T 26300L 48 SW SVC
H01FJE	HPE Aruba Networking Foundational Care 1Y 24x7 with CDMR 6300L 24 SW SVC
H01MPE	HPE Aruba Networking Foundational Care 1Y 24x7 with CDMR 6300L 48 SW SVC
HR6D5E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6300F 24 PoE Switch SVC
HR6W5E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6300F 24 Switch SVC
HR5V0E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6300F 48 PoE Switch SVC
HR6N0E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6300F 48 Switch SVC
HR5H3E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6300M 24 PoE Switch SVC
HL5Y0E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6300M 24 SR PoE Switch SVC
HL7H3E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6300M 24 Switch SVC
HR4B9E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6300M 24SFP Switch SVC
HL6L4E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6300M 48 PoE Switch SVC

HR4Q3E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6300M 48 SR PoE Switch SVC
HR5M2E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6300M 48 Switch SVC
H58Z7E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6300M 48 Switch SVC
HR6D6E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6300F 24 PoE Switch SVC
HR6W6E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6300F 24 Switch SVC
HR5V1E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6300F 48 PoE Switch SVC
HR6N1E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6300F 48 Switch SVC
HR5H4E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6300M 24 PoE Switch SVC
HL5Y1E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6300M 24 SR PoE Switch SVC
HL7H4E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6300M 24 Switch SVC
HR4COE	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6300M 24SFP Switch SVC
HR4Y9E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6300M 48 PoE Switch SVC
HR4Q4E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6300M 48 SR PoE Switch SVC
HR5M3E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6300M 48 Switch SVC
H58Z8E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6300M 48 Switch SVC
H01FLE	HPE Aruba Networking Foundational Care 1Y CTR 6300L 24 SW SVC
H01MRE	HPE Aruba Networking Foundational Care 1Y CTR 6300L 48 SW SVC
H08MYE	HPE Aruba Networking Foundational Care 1Y CTR 6300M 16p CL8 Swch Service
H63C1E	HPE Aruba Networking Foundational Care 1Y CTR 6300M 24SR PoE SVC
H08RXE	HPE Aruba Networking Foundational Care 1Y CTR 6300M 24p 1G Fib Swch Service
H64E3E	HPE Aruba Networking Foundational Care 1Y CTR 6300M 24p SFP+ LRM SVC
H08WWE	HPE Aruba Networking Foundational Care 1Y CTR 6300M 32p CL8 Swch Service
H14GZE	HPE Aruba Networking Foundational Care 1Y CTR 6300M 48SR10 Swch Service
H14LVE	HPE Aruba Networking Foundational Care 1Y CTR 6300M 48SR10 TAA Swch Service
H09BVE	HPE Aruba Networking Foundational Care 1Y CTR 6300M 48p 1G Fib Swch Service
H63R2E	HPE Aruba Networking Foundational Care 1Y CTR 6300M 48p SR5 PoE SVC
H08MZE	HPE Aruba Networking Foundational Care 1Y CTR CDMR 6300M 16p CL8 Swch Service
H63C2E	HPE Aruba Networking Foundational Care 1Y CTR CDMR 6300M 24SR PoE SVC
H08RYE	HPE Aruba Networking Foundational Care 1Y CTR CDMR 6300M 24p 1G Fib Swch Service
H64E4E	HPE Aruba Networking Foundational Care 1Y CTR CDMR 6300M 24p SFP+ LRM SVC
H08WXE	HPE Aruba Networking Foundational Care 1Y CTR CDMR 6300M 32p CL8 Swch Service
H14HBE	HPE Aruba Networking Foundational Care 1Y CTR CDMR 6300M 48SR10 Swch Service
H14LWE	HPE Aruba Networking Foundational Care 1Y CTR CDMR 6300M 48SR10 TAA Swch Service
H09BWE	HPE Aruba Networking Foundational Care 1Y CTR CDMR 6300M 48p 1G Fib Swch Service
H63R3E	HPE Aruba Networking Foundational Care 1Y CTR CDMR 6300M 48p SR5 PoE SVC
H01FME	HPE Aruba Networking Foundational Care 1Y CTR with CDMR 6300L 24 SW SVC

H01MSE	HPE Aruba Networking Foundational Care 1Y CTR with CDMR 6300L 48 SW SVC
H01FDE	HPE Aruba Networking Foundational Care 1Y NBD 6300L 24 SW SVC
H01MKE	HPE Aruba Networking Foundational Care 1Y NBD 6300L 48 SW SVC
H08MRE	HPE Aruba Networking Foundational Care 1Y NBD 6300M 16p CL8 Swch Service
H63B5E	HPE Aruba Networking Foundational Care 1Y NBD 6300M 24SR PoE SVC
H08RQE	HPE Aruba Networking Foundational Care 1Y NBD 6300M 24p 1G Fib Swch Service
H64D7E	HPE Aruba Networking Foundational Care 1Y NBD 6300M 24p SFP+ LRM SVC
H08WNE	HPE Aruba Networking Foundational Care 1Y NBD 6300M 32p CL8 Swch Service
H09BME	HPE Aruba Networking Foundational Care 1Y NBD 6300M 48p 1G Fib Swch Service
H63Q6E	HPE Aruba Networking Foundational Care 1Y NBD 6300M 48p SR5 PoE SVC
H08MSE	HPE Aruba Networking Foundational Care 1Y NBD CDMR 6300M 16p CL8 Swch Service
H63B6E	HPE Aruba Networking Foundational Care 1Y NBD CDMR 6300M 24SR PoE SVC
H08RRE	HPE Aruba Networking Foundational Care 1Y NBD CDMR 6300M 24p 1G Fib Swch Service
H64D8E	HPE Aruba Networking Foundational Care 1Y NBD CDMR 6300M 24p SFP+ LRM SVC
H08WQE	HPE Aruba Networking Foundational Care 1Y NBD CDMR 6300M 32p CL8 Swch Service
H09BNE	HPE Aruba Networking Foundational Care 1Y NBD CDMR 6300M 48p 1G Fib Swch Service
H63Q7E	HPE Aruba Networking Foundational Care 1Y NBD CDMR 6300M 48p SR5 PoE SVC
HR6C6E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300F 24 PoE Switch SVC
HR6V6E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300F 24 Switch SVC
HR5U1E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300F 48 PoE Switch SVC
HL8D3E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300F 48 Switch SVC
H01DZE	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300L 24 SW SVC
H01MGE	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300L 48 SW SVC
H08MME	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 16p CL8 Swch Service
HL5X1E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 24 SR PoE Switch SVC
HL7G4E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 24 Switch SVC
HR4B0E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 24SFP Switch SVC
H63B2E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 24SR PoE SVC
H08RLE	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 24p 1G Fib Swch Service
H64D4E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 24p SFP+ LRM SVC
H08WKE	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 32p CL8 Swch Service
HL6K5E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 48 PoE Switch SVC
HL6F6E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 48 SR PoE Switch SVC
H58Y9E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 48 Switch SVC
HR5L3E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 48 Switch SVC
H14GQE	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 48SR10 Swch Service

H14LKE	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 48SR10 TAA Swch Service
H09BJE	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 48p 1G Fib Swch Service
H63Q3E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6300M 48p SR5 PoE SVC
HR5G4E	HPE Aruba Networking Foundational Care 1Y NBD Exch HPE Aruba Networking 6300M 24P PoE SVC
H08MNE	HPE Aruba Networking Foundational Care 1Y NBD Exch HW Only 6300M 16p CL8 Swch Service
H08RME	HPE Aruba Networking Foundational Care 1Y NBD Exch HW Only 6300M 24p 1G Fib Swch Service
H08WLE	HPE Aruba Networking Foundational Care 1Y NBD Exch HW Only 6300M 32p CL8 Swch Service
H14GRE	HPE Aruba Networking Foundational Care 1Y NBD Exch HW Only 6300M 48SR10 Swch Service
H14LLE	HPE Aruba Networking Foundational Care 1Y NBD Exch HW Only 6300M 48SR10 TAA Swch Service
H09BKE	HPE Aruba Networking Foundational Care 1Y NBD Exch HW Only 6300M 48p 1G Fib Swch Service
HR6C7E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300F 24 PoE Switch SVC
HR6V7E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300F 24 Switch SVC
HR5U2E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300F 48 PoE Switch SVC
HL8D4E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300F 48 Switch SVC
H01FBE	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300L 24 SW SVC
H01MHE	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300L 48 SW SVC
HR5G5E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300M 24 PoE Switch SVC
HL5X2E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300M 24 SR PoE Switch SVC
HL7G5E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300M 24 Switch SVC
HR4B1E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300M 24SFP Switch SVC
H63B3E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300M 24SR PoE SVC
H64D5E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300M 24p SFP+ LRM SVC
HL6K6E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300M 48 PoE Switch SVC
HR5L4E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300M 48 Switch SVC
H58Z0E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300M 48 Switch SVC
H63Q4E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6300M 48p SR5 PoE SVC
HR6J8E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300F 24 PoE Switch SVC
HR7B8E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300F 24 Switch SVC
HR6A3E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300F 48 PoE Switch SVC
HL8E9E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300F 48 Switch SVC
H01HYE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300L 24 SW SVC
H01QFE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300L 48 SW SVC
H08PHE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 16p CL8 Swch Service
HL6V6E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 24 PoE Switch SVC
HR4M1E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 24 SR PoE Switch SVC
HL7N6E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 24 Switch SVC

HL5U8E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 24SFP Switch SVC
H63H4E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 24SR PoE SVC
H08TGE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 24p 1G Fib Swch Service
H64K6E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 24p SFP+ LRM SVC
H08YFE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 32p CL8 Swch Service
HL6M1E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 48 PoE Switch SVC
HR4V6E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 48 SR PoE Switch SVC
H58W6E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 48 Switch SVC
HL7E1E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 48 Switch SVC
H14JGE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 48SR10 Swch Service
H14NBE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 48SR10 TAA Swch Service
H09DDE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 48p 1G Fib Swch Service
H63W5E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6300M 48p SR5 PoE SVC
HR6J9E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300F 24 PoE Switch SVC
HR7B9E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300F 24 Switch SVC
HR6A4E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300F 48 PoE Switch SVC
HL8F0E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300F 48 Switch SVC
H01HZE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300L 24 SW SVC
H01QGE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300L 48 SW SVC
H08PJE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 16p CL8 Swch Service
HL6V7E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 24 PoE Switch SVC
HR4M2E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 24 SR PoE Switch SVC
HL7N7E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 24 Switch SVC
HL5U9E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 24SFP Switch SVC
H63H5E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 24SR PoE SVC
H08THE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 24p 1G Fib Swch Service
H64K7E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 24p SFP+ LRM SVC
H08YGE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 32p CL8 Swch Service
HL6M2E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 48 PoE Switch SVC
HR4V7E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 48 SR PoE Switch SVC
H58W7E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 48 Switch SVC
HL7E2E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 48 Switch SVC
H14JHE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 48SR10 Swch Service
H14NCE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 48SR10 TAA Swch Service
H09DFE	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 48p 1G Fib Swch Service
H63W6E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6300M 48p SR5 PoE SVC

HR6C9E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6300F 24 PoE Switch SVC
HR6V9E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6300F 24 Switch SVC
HR5U4E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6300F 48 PoE Switch SVC
HL8D6E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6300F 48 Switch SVC
HR5G7E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6300M 24 PoE Switch SVC
HL5X4E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6300M 24 SR PoE Switch SVC
HL7G7E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6300M 24 Switch SVC
HR4B3E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6300M 24SFP Switch SVC
HL6K8E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6300M 48 PoE Switch SVC
HR4P7E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6300M 48 SR PoE Switch SVC
H68D5E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6300M 48 Switch SVC
H68D9E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6300M 48 Switch SVC
H14GTE	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6300M 48SR10 Swch Service
H14LNE	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6300M 48SR10 TAA Swch Service
HR6D0E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6300F 24 PoE Switch SVC
HR6W0E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6300F 24 Switch SVC
H68D6E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6300F 48 PoE Switch SVC
HL8D7E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6300F 48 Switch SVC
HR5G8E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6300M 24 PoE Switch SVC
HL5X5E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6300M 24 SR PoE Switch SVC
HL7G8E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6300M 24 Switch SVC
HR4B4E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6300M 24SFP Switch SVC
HL6K9E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6300M 48 PoE Switch SVC
HR4P8E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6300M 48 SR PoE Switch SVC
H58Z2E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6300M 48 Switch SVC
HR5L7E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6300M 48 Switch SVC
H14GVE	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6300M 48SR10 Swch Service
H14LQE	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6300M 48SR10 TAA Swch Service
H01FFE	HPE Aruba Networking Foundational Care 1Y NBD with CDMR 6300L 24 SW SVC
H01MLE	HPE Aruba Networking Foundational Care 1Y NBD with CDMR 6300L 48 SW SVC
H14GYE	HPE Aruba Networking Foundational Care 1Y SW + Technical Support 6300M 48SR10 Swch Service
H14LTE	HPE Aruba Networking Foundational Care 1Y SW + Technical Support 6300M 48SR10 TAA Swch Service
H14JSE	HPE Aruba Networking Foundational Care 1Y SW + Technical Support Vol T2 6300M 48SR10 Swch Service
H14NME	HPE Aruba Networking Foundational Care 1Y SW + Technical Support Vol T2 6300M 48SR10 TAA Swch Service
H01FQE	HPE Aruba Networking Foundational Care 3Y 4-Hour Exch 6300L 24 SW SVC

H01MWE	HPE Aruba Networking Foundational Care 3Y 4-Hour Exch 6300L 48 SW SVC
H01JVE	HPE Aruba Networking Foundational Care 3Y 4-Hour Exch Vol T1 6300L 24 SW SVC
H01RBE	HPE Aruba Networking Foundational Care 3Y 4-Hour Exch Vol T1 6300L 48 SW SVC
H01JWE	HPE Aruba Networking Foundational Care 3Y 4-Hour Exch Vol T2 6300L 24 SW SVC
H01RCE	HPE Aruba Networking Foundational Care 3Y 4-Hour Exch Vol T2 6300L 48 SW SVC
H01FXE	HPE Aruba Networking Foundational Care 3Y 4-Hour Onsite 6300L 24 SW SVC
H01NDE	HPE Aruba Networking Foundational Care 3Y 4-Hour Onsite 6300L 48 SW SVC
H01FWE	HPE Aruba Networking Foundational Care 3Y 4-Hour Onsite Hardware Only 6300L 24 SW SVC
H01NCE	HPE Aruba Networking Foundational Care 3Y 4-Hour Onsite Hardware Only 6300L 48 SW SVC
HR6D9E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300F 24 PoE Switch SVC
HR6W9E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300F 24 Switch SVC
HR5V4E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300F 48 PoE Switch SVC
HR6N4E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300F 48 Switch SVC
H08NDE	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 16p CL8 Swch Service
HR5H7E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 24 PoE Switch SVC
HL5Y4E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 24 SR PoE Switch SVC
HL7H7E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 24 Switch SVC
HR4C3E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 24SFP Switch SVC
H63C5E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 24SR PoE SVC
H08SCE	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 24p 1G Fib Swch Service
H64E7E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 24p SFP+ LRM SVC
H08XBE	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 32p CL8 Swch Service
HR4Z2E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 48 PoE Switch SVC
HR4Q7E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 48 SR PoE Switch SVC
HR5M6E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 48 Switch SVC
H59A1E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 48 Switch SVC
H14HFE	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 48SR10 Swch Service
H14LZE	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 48SR10 TAA Swch Service
H09BZE	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 48p 1G Fib Swch Service
H63R6E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6300M 48p SR5 PoE SVC
HR6L6E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300F 24 PoE Switch SVC
HR7D6E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300F 24 Switch SVC
HR6C1E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300F 48 PoE Switch SVC
HL8G7E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300F 48 Switch SVC
H08QFE	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 16p CL8 Swch Service
HL6X4E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 24 PoE Switch SVC

HR4N9E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 24 SR PoE Switch SVC
HL7Q4E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 24 Switch SVC
HL5W6E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 24SFP Switch SVC
H63K2E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 24SR PoE SVC
H08VDE	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 24p 1G Fib Swch Service
H64M4E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 24p SFP+ LRM SVC
H08ZCE	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 32p CL8 Swch Service
HL6N9E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 48 PoE Switch SVC
HR4X4E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 48 SR PoE Switch SVC
H59C2E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 48 Switch SVC
HR5P7E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 48 Switch SVC
H14KDE	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 48SR10 Swch Service
H14NYE	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 48SR10 TAA Swch Service
H09FBE	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 48p 1G Fib Swch Service
H63Y3E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6300M 48p SR5 PoE SVC
HR6L7E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300F 24 PoE Switch SVC
HR7D7E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300F 24 Switch SVC
HR6C2E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300F 48 PoE Switch SVC
HL8G8E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300F 48 Switch SVC
H08QGE	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 16p CL8 Swch Service
HL6X5E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 24 PoE Switch SVC
HR4POE	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 24 SR PoE Switch SVC
HL7Q5E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 24 Switch SVC
HR4E5E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 24SFP Switch SVC
H63K3E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 24SR PoE SVC
H08VFE	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 24p 1G Fib Swch Service
H64M5E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 24p SFP+ LRM SVC
H08ZDE	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 32p CL8 Swch Service
HL6POE	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 48 PoE Switch SVC
HR4X5E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 48 SR PoE Switch SVC
HR5P8E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 48 Switch SVC
H59C3E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 48 Switch SVC
H14KFE	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 48SR10 Swch Service
H14NZE	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 48SR10 TAA Swch Service
H09FCE	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 48p 1G Fib Swch Service
H63Y4E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6300M 48p SR5 PoE SVC

H08VLE	HPE Aruba Networking Foundational Care 3Y 4HR OS Technical Support V T2 6300M 24p 1GFib Swch Service
H09FJE	HPE Aruba Networking Foundational Care 3Y 4HR OS Technical Support V T2 6300M 48p 1GFib Swch Service
H08QME	HPE Aruba Networking Foundational Care 3Y 4HR OS Technical Support Vol T2 6300M 16p CL8 Swch Service
H08ZKE	HPE Aruba Networking Foundational Care 3Y 4HR OS Technical Support Vol T2 6300M 32p CL8 Swch Service
HR6E5E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300F 24 PoE Switch SVC
HR6X5E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300F 24 Switch SVC
HR5W0E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300F 48 PoE Switch SVC
HR6P0E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300F 48 Switch SVC
H08NKE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 16p CL8 Swch Service
HL6R3E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 24 PoE Switch SVC
HL5Z0E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 24 SR PoE Switch SVC
HL7J3E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 24 Switch SVC
HR4C9E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 24SFP Switch SVC
H63D1E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 24SR PoE SVC
H08SJE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 24p 1G Fib Swch Service
H64F3E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 24p SFP+ LRM SVC
H08XHE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 32p CL8 Swch Service
HR4Z8E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 48 PoE Switch SVC
HR4R3E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 48 SR PoE Switch SVC
H59A7E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 48 Switch SVC
HR5N2E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 48 Switch SVC
H14HKE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 48SR10 Swch Service
H14MFE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 48SR10 TAA Swch Service
H09CGE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 48p 1G Fib Swch Service
H63S2E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6300M 48p SR5 PoE SVC
HR6E6E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300F 24 PoE Switch SVC
HR6X6E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300F 24 Switch SVC
HR5W1E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300F 48 PoE Switch SVC
HR6P1E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300F 48 Switch SVC
H08NLE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300M 16p CL8 Swch Service
HL6R4E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300M 24 PoE Switch SVC
HL5Z1E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300M 24 SR PoE Switch SVC
HL7J4E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300M 24 Switch SVC
HR4D0E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300M 24SFP Switch SVC

H08SKE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300M 24p 1G Fib Swch Service
H08XJE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300M 32p CL8 Swch Service
HR4Z9E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300M 48 PoE Switch SVC
HR4R4E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300M 48 SR PoE Switch SVC
HR5N3E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300M 48 Switch SVC
H59A8E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300M 48 Switch SVC
H14HLE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300M 48SR10 Swch Service
H14MGE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300M 48SR10 TAA Swch Service
H09CHE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6300M 48p 1G Fib Swch Service
H08NJE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite HW Only 6300M 16p CL8 Swch Service
H08SHE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite HW Only 6300M 24p 1G Fib Swch Service
H08XGE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite HW Only 6300M 32p CL8 Swch Service
H09CFE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite HW Only 6300M 48p 1G Fib Swch Service
HR6E4E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300F 24 PoE Switch SVC
HR6X4E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300F 24 Switch SVC
HR5V9E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300F 48 PoE Switch SVC
HR6N9E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300F 48 Switch SVC
HL6R2E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300M 24 PoE Switch SVC
HL5Y9E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300M 24 SR PoE Switch SVC
HL7J2E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300M 24 Switch SVC
HR4C8E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300M 24SFP Switch SVC
H63D0E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300M 24SR PoE SVC
H64F2E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300M 24p SFP+ LRM SVC
HR4Z7E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300M 48 PoE Switch SVC
HR4R2E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300M 48 SR PoE Switch SVC
HR5N1E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300M 48 Switch SVC
H59A6E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300M 48 Switch SVC
H63S1E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6300M 48p SR5 PoE SVC
H08NME	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Technical Support 6300M 16p CL8 Swch Service
H08SLE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Technical Support 6300M 24p 1G Fib Swch Service
H08XKE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Technical Support 6300M 32p CL8 Swch Service
H09CJE	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Technical Support 6300M 48p 1G Fib Swch Service
H63D2E	HPE Aruba Networking Foundational Care 3Y 24x7 CDMR 6300M 24SR PoE SVC

H64F4E	HPE Aruba Networking Foundational Care 3Y 24x7 CDMR 6300M 24p SFP+ LRM SVC
H63S3E	HPE Aruba Networking Foundational Care 3Y 24x7 CDMR 6300M 48p SR5 PoE SVC
H01FZE	HPE Aruba Networking Foundational Care 3Y 24x7 Technical Support 6300L 24 SW SVC
H01NGE	HPE Aruba Networking Foundational Care 3Y 24x7 Technical Support 6300L 48 SW SVC
H01KCE	HPE Aruba Networking Foundational Care 3Y 24x7 Technical Support Vol T 26300L 24 SW SVC
H01RJE	HPE Aruba Networking Foundational Care 3Y 24x7 Technical Support Vol T 26300L 48 SW SVC
H01FYE	HPE Aruba Networking Foundational Care 3Y 24x7 with CDMR 6300L 24 SW SVC
H01NFE	HPE Aruba Networking Foundational Care 3Y 24x7 with CDMR 6300L 48 SW SVC
HR6E8E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6300F 24 PoE Switch SVC
HR6X8E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6300F 24 Switch SVC
HR5W3E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6300F 48 PoE Switch SVC
HR6P3E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6300F 48 Switch SVC
HL6R6E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6300M 24 PoE Switch SVC
HL5Z3E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6300M 24 SR PoE Switch SVC
HL7J6E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6300M 24 Switch SVC
HR4D2E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6300M 24SFP Switch SVC
HR5A1E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6300M 48 PoE Switch SVC
HR4R6E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6300M 48 SR PoE Switch SVC
HR5N5E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6300M 48 Switch SVC
H59B0E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6300M 48 Switch SVC
HR6E9E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6300F 24 PoE Switch SVC
HR6X9E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6300F 24 Switch SVC
HR5W4E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6300F 48 PoE Switch SVC
HR6P4E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6300F 48 Switch SVC
HL6R7E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6300M 24 PoE Switch SVC
HL5Z4E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6300M 24 SR PoE Switch SVC
HL7J7E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6300M 24 Switch SVC
HR4D3E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6300M 24SFP Switch SVC
HR5A2E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6300M 48 PoE Switch SVC
HR4R7E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6300M 48 SR PoE Switch SVC
HR5N6E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6300M 48 Switch SVC
H59B1E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6300M 48 Switch SVC
H01GBE	HPE Aruba Networking Foundational Care 3Y CTR 6300L 24 SW SVC
H01NHE	HPE Aruba Networking Foundational Care 3Y CTR 6300L 48 SW SVC
H08NNE	HPE Aruba Networking Foundational Care 3Y CTR 6300M 16p CL8 Swch Service
H63D4E	HPE Aruba Networking Foundational Care 3Y CTR 6300M 24SR PoE SVC

H08SME	HPE Aruba Networking Foundational Care 3Y CTR 6300M 24p 1G Fib Swch Service
H64F6E	HPE Aruba Networking Foundational Care 3Y CTR 6300M 24p SFP+ LRM SVC
H08XLE	HPE Aruba Networking Foundational Care 3Y CTR 6300M 32p CL8 Swch Service
H14HNE	HPE Aruba Networking Foundational Care 3Y CTR 6300M 48SR10 Swch Service
H14MJE	HPE Aruba Networking Foundational Care 3Y CTR 6300M 48SR10 TAA Swch Service
H09CKE	HPE Aruba Networking Foundational Care 3Y CTR 6300M 48p 1G Fib Swch Service
H63S5E	HPE Aruba Networking Foundational Care 3Y CTR 6300M 48p SR5 PoE SVC
H08NQE	HPE Aruba Networking Foundational Care 3Y CTR CDMR 6300M 16p CL8 Swch Service
H63D5E	HPE Aruba Networking Foundational Care 3Y CTR CDMR 6300M 24SR PoE SVC
H08SNE	HPE Aruba Networking Foundational Care 3Y CTR CDMR 6300M 24p 1G Fib Swch Service
H64F7E	HPE Aruba Networking Foundational Care 3Y CTR CDMR 6300M 24p SFP+ LRM SVC
H08XME	HPE Aruba Networking Foundational Care 3Y CTR CDMR 6300M 32p CL8 Swch Service
H14HQE	HPE Aruba Networking Foundational Care 3Y CTR CDMR 6300M 48SR10 Swch Service
H14MKE	HPE Aruba Networking Foundational Care 3Y CTR CDMR 6300M 48SR10 TAA Swch Service
H09CLE	HPE Aruba Networking Foundational Care 3Y CTR CDMR 6300M 48p 1G Fib Swch Service
H63S6E	HPE Aruba Networking Foundational Care 3Y CTR CDMR 6300M 48p SR5 PoE SVC
H01GCE	HPE Aruba Networking Foundational Care 3Y CTR with CDMR 6300L 24 SW SVC
H01NJE	HPE Aruba Networking Foundational Care 3Y CTR with CDMR 6300L 48 SW SVC
H01FRE	HPE Aruba Networking Foundational Care 3Y NBD 6300L 24 SW SVC
H01MXE	HPE Aruba Networking Foundational Care 3Y NBD 6300L 48 SW SVC
H08NFE	HPE Aruba Networking Foundational Care 3Y NBD 6300M 16p CL8 Swch Service
H63C6E	HPE Aruba Networking Foundational Care 3Y NBD 6300M 24SR PoE SVC
H08SDE	HPE Aruba Networking Foundational Care 3Y NBD 6300M 24p 1G Fib Swch Service
H64E8E	HPE Aruba Networking Foundational Care 3Y NBD 6300M 24p SFP+ LRM SVC
H08XCE	HPE Aruba Networking Foundational Care 3Y NBD 6300M 32p CL8 Swch Service
H09CBE	HPE Aruba Networking Foundational Care 3Y NBD 6300M 48p 1G Fib Swch Service
H63R7E	HPE Aruba Networking Foundational Care 3Y NBD 6300M 48p SR5 PoE SVC
H08NGE	HPE Aruba Networking Foundational Care 3Y NBD CDMR 6300M 16p CL8 Swch Service
H63C7E	HPE Aruba Networking Foundational Care 3Y NBD CDMR 6300M 24SR PoE SVC
H08SFE	HPE Aruba Networking Foundational Care 3Y NBD CDMR 6300M 24p 1G Fib Swch Service
H64E9E	HPE Aruba Networking Foundational Care 3Y NBD CDMR 6300M 24p SFP+ LRM SVC
H08XDE	HPE Aruba Networking Foundational Care 3Y NBD CDMR 6300M 32p CL8 Swch Service
H09CCE	HPE Aruba Networking Foundational Care 3Y NBD CDMR 6300M 48p 1G Fib Swch Service
H63R8E	HPE Aruba Networking Foundational Care 3Y NBD CDMR 6300M 48p SR5 PoE SVC
HR6D8E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300F 24 PoE Switch SVC
HR6W8E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300F 24 Switch SVC

HR5V3E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300F 48 PoE Switch SVC
HR6N3E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300F 48 Switch SVC
H01FPE	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300L 24 SW SVC
H01MVE	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300L 48 SW SVC
H08NCE	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 16p CL8 Swch Service
HR5H6E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 24 PoE Switch SVC
HL5Y3E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 24 SR PoE Switch SVC
HL7H6E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 24 Switch SVC
HR4C2E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 24SFP Switch SVC
H63C4E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 24SR PoE SVC
H08SBE	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 24p 1G Fib Swch Service
H64E6E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 24p SFP+ LRM SVC
H08WZE	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 32p CL8 Swch Service
HR4Z1E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 48 PoE Switch SVC
HR4Q6E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 48 SR PoE Switch SVC
HR5M5E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 48 Switch SVC
H59A0E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 48 Switch SVC
H14HDE	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 48SR10 Swch Service
H14LYE	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 48SR10 TAA Swch Service
H09BYE	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 48p 1G Fib Swch Service
H63R5E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6300M 48p SR5 PoE SVC
H08NBE	HPE Aruba Networking Foundational Care 3Y NBD Exch HW Only 6300M 16p CL8 Swch Service
H08RZE	HPE Aruba Networking Foundational Care 3Y NBD Exch HW Only 6300M 24p 1G Fib Swch Service
H08WYE	HPE Aruba Networking Foundational Care 3Y NBD Exch HW Only 6300M 32p CL8 Swch Service
H14HCE	HPE Aruba Networking Foundational Care 3Y NBD Exch HW Only 6300M 48SR10 Swch Service
H14LXE	HPE Aruba Networking Foundational Care 3Y NBD Exch HW Only 6300M 48SR10 TAA Swch Service
H09BXE	HPE Aruba Networking Foundational Care 3Y NBD Exch HW Only 6300M 48p 1G Fib Swch Service
HR6D7E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300F 24 PoE Switch SVC
HR6W7E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300F 24 Switch SVC
HR5V2E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300F 48 PoE Switch SVC
HR6N2E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300F 48 Switch SVC
H01FNE	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300L 24 SW SVC
H01MTE	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300L 48 SW SVC
HR5H5E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300M 24 PoE Switch SVC
HL5Y2E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300M 24 SR PoE Switch SVC
HL7H5E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300M 24 Switch SVC

HR4C1E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300M 24SFP Switch SVC
H63C3E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300M 24SR PoE SVC
H64E5E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300M 24p SFP+ LRM SVC
HR4Z0E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300M 48 PoE Switch SVC
HR4Q5E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300M 48 SR PoE Switch SVC
HR5M4E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300M 48 Switch SVC
H58Z9E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300M 48 Switch SVC
H63R4E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6300M 48p SR5 PoE SVC
HR6L2E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300F 24 PoE Switch SVC
HR7D2E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300F 24 Switch SVC
HR6B7E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300F 48 PoE Switch SVC
HL8G3E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300F 48 Switch SVC
H01JQE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300L 24 SW SVC
H01QWE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300L 48 SW SVC
H08PZE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 16p CL8 Swch Service
HL6X0E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 24 PoE Switch SVC
HR4N5E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 24 SR PoE Switch SVC
HL7Q0E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 24 Switch SVC
HL5W2E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 24SFP Switch SVC
H63J8E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 24SR PoE SVC
H08TYE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 24p 1G Fib Swch Service
H64M0E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 24p SFP+ LRM SVC
H08YXE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 32p CL8 Swch Service
HL6N5E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 48 PoE Switch SVC
HR4X0E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 48 SR PoE Switch SVC
H59B8E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 48 Switch SVC
HR5P3E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 48 Switch SVC
H14JYE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 48SR10 Swch Service
H14NTE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 48SR10 TAA Swch Service
H09DWE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 48p 1G Fib Swch Service
H63X9E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6300M 48p SR5 PoE SVC
HR6L3E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300F 24 PoE Switch SVC
HR7D3E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300F 24 Switch SVC
HR6B8E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300F 48 PoE Switch SVC
HL8G4E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300F 48 Switch SVC
H01JRE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300L 24 SW SVC

H01QXE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300L 48 SW SVC
H08QBE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 16p CL8 Swch Service
HL6X1E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 24 PoE Switch SVC
HR4N6E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 24 SR PoE Switch SVC
HL7Q1E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 24 Switch SVC
HL5W3E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 24SFP Switch SVC
H63J9E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 24SR PoE SVC
H08TZE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 24p 1G Fib Swch Service
H64M1E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 24p SFP+ LRM SVC
H08YYE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 32p CL8 Swch Service
HL6N6E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 48 PoE Switch SVC
HR4X1E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 48 SR PoE Switch SVC
H59B9E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 48 Switch SVC
HR5P4E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 48 Switch SVC
H14JZE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 48SR10 Swch Service
H14NVE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 48SR10 TAA Swch Service
H09DXE	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 48p 1G Fib Swch Service
H63Y0E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6300M 48p SR5 PoE SVC
HR6E0E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6300F 24 PoE Switch SVC
HR6X0E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6300F 24 Switch SVC
HR5V5E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6300F 48 PoE Switch SVC
HR6N5E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6300F 48 Switch SVC
HR5H8E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6300M 24 PoE Switch SVC
HL5Y5E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6300M 24 SR PoE Switch SVC
HL7H8E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6300M 24 Switch SVC
HR4C4E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6300M 24SFP Switch SVC
HR4Z3E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6300M 48 PoE Switch SVC
HR4Q8E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6300M 48 SR PoE Switch SVC
H59A2E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6300M 48 Switch SVC
HR5M7E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6300M 48 Switch SVC
H14HGE	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6300M 48SR10 Swch Service
H14MBE	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6300M 48SR10 TAA Swch Service
HR6E1E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6300F 24 PoE Switch SVC
HR6X1E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6300F 24 Switch SVC
HR5V6E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6300F 48 PoE Switch SVC
HR6N6E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6300F 48 Switch SVC

HR5H9E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6300M 24 PoE Switch SVC
HL5Y6E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6300M 24 SR PoE Switch SVC
HL7H9E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6300M 24 Switch SVC
HR4C5E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6300M 24SFP Switch SVC
HR4Z4E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6300M 48 PoE Switch SVC
HR4Q9E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6300M 48 SR PoE Switch SVC
HR5M8E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6300M 48 Switch SVC
H59A3E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6300M 48 Switch SVC
H14HHE	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6300M 48SR10 Swch Service
H14MCE	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6300M 48SR10 TAA Swch Service
H01FSE	HPE Aruba Networking Foundational Care 3Y NBD with CDMR 6300L 24 SW SVC
H01MYE	HPE Aruba Networking Foundational Care 3Y NBD with CDMR 6300L 48 SW SVC
H14HME	HPE Aruba Networking Foundational Care 3Y SW + Technical Support 6300M 48SR10 Swch Service
H14MHE	HPE Aruba Networking Foundational Care 3Y SW + Technical Support 6300M 48SR10 TAA Swch Service
H14KLE	HPE Aruba Networking Foundational Care 3Y SW + Technical Support Vol T2 6300M 48SR10 Swch Service
H14PGE	HPE Aruba Networking Foundational Care 3Y SW +Technical Support Vol T2 6300M 48SR10 TAA Swch Service
H58TOE	HPE Aruba Networking Foundational Care 4Y 4HR Exch 6300M 48 Switch SVC
H59D7E	HPE Aruba Networking Foundational Care 4Y 4HR Exch Vol T1 6300M 48 Switch SVC
H59D8E	HPE Aruba Networking Foundational Care 4Y 4HR Exch Vol T2 6300M 48 Switch SVC
H58T6E	HPE Aruba Networking Foundational Care 4Y 4HR Onsite 6300M 48 Switch SVC
H58T7E	HPE Aruba Networking Foundational Care 4Y 4HR Onsite CDMR 6300M 48 Switch SVC
H58T5E	HPE Aruba Networking Foundational Care 4Y 4HR Onsite Hardware Only 6300M 48 Switch SVC
H58T9E	HPE Aruba Networking Foundational Care 4Y CTR 6-Hour 6300M 48 Switch SVC
H58U0E	HPE Aruba Networking Foundational Care 4Y CTR 6-Hour CDMR 6300M 48 Switch SVC
H58S9E	HPE Aruba Networking Foundational Care 4Y NBD Exch 6300M 48 Switch SVC
H58S8E	HPE Aruba Networking Foundational Care 4Y NBD Exch Hardware Only 6300M 48 Switch SVC
H59D3E	HPE Aruba Networking Foundational Care 4Y NBD Exch Vol T1 6300M 48 Switch SVC
H59D4E	HPE Aruba Networking Foundational Care 4Y NBD Exch Vol T2 6300M 48 Switch SVC
H58T1E	HPE Aruba Networking Foundational Care 4Y NBD Onsite 6300M 48 Switch SVC
H58T2E	HPE Aruba Networking Foundational Care 4Y NBD Onsite CDMR 6300M 48 Switch SVC
H01GWE	HPE Aruba Networking Foundational Care 5Y 4-Hour Exch 6300L 24 SW SVC
H01PCE	HPE Aruba Networking Foundational Care 5Y 4-Hour Exch 6300L 48 SW SVC
H01LGE	HPE Aruba Networking Foundational Care 5Y 4-Hour Exch Vol T1 6300L 24 SW SVC
H01SME	HPE Aruba Networking Foundational Care 5Y 4-Hour Exch Vol T1 6300L 48 SW SVC
H01LHE	HPE Aruba Networking Foundational Care 5Y 4-Hour Exch Vol T2 6300L 24 SW SVC

H01SNE	HPE Aruba Networking Foundational Care 5Y 4-Hour Exch Vol T2 6300L 48 SW SVC
H01HDE	HPE Aruba Networking Foundational Care 5Y 4-Hour Onsite 6300L 24 SW SVC
H01PKE	HPE Aruba Networking Foundational Care 5Y 4-Hour Onsite 6300L 48 SW SVC
H01HCE	HPE Aruba Networking Foundational Care 5Y 4-Hour Onsite Hardware Only 6300L 24 SW SVC
H01PJE	HPE Aruba Networking Foundational Care 5Y 4-Hour Onsite Hardware Only 6300L 48 SW SVC
HR6G5E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300F 24 PoE Switch SVC
HR6Z5E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300F 24 Switch SVC
HR5YOE	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300F 48 PoE Switch SVC
HR6ROE	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300F 48 Switch SVC
H08NTE	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 16p CL8 Swch Service
HL6T3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 24 PoE Switch SVC
HL6B0E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 24 SR PoE Switch SVC
HL7L3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 24 Switch SVC
HL5S5E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 24SFP Switch SVC
H63F1E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 24SR PoE SVC
H08SSE	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 24p 1G Fib Swch Service
H64H3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 24p SFP+ LRM SVC
H08XRE	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 32p CL8 Swch Service
HR5B8E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 48 PoE Switch SVC
HR4T3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 48 SR PoE Switch SVC
HL7B8E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 48 Switch SVC
H58U3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 48 Switch SVC
H14HTE	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 48SR10 Swch Service
H14MNE	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 48SR10 TAA Swch Service
H09CQE	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 48p 1G Fib Swch Service
H63U2E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6300M 48p SR5 PoE SVC
HL8B2E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300F 24 PoE Switch SVC
HL8K0E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300F 24 Switch SVC
HL7X3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300F 48 PoE Switch SVC
HR6T5E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300F 48 Switch SVC
H08QYE	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 16p CL8 Swch Service
HR5J2E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 24 PoE Switch SVC
HL6D5E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 24 SR PoE Switch SVC
HL7T4E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 24 Switch SVC
HR4H4E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 24SFP Switch SVC
H63N2E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 24SR PoE SVC

H08VXE	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 24p 1G Fib Swch Service
H64Q4E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 24p SFP+ LRM SVC
H08ZWE	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 32p CL8 Swch Service
HR5E3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 48 PoE Switch SVC
HL6H4E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 48 SR PoE Switch SVC
HR5S7E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 48 Switch SVC
H59F2E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 48 Switch SVC
H14KXE	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 48SR10 Swch Service
H14PSE	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 48SR10 TAA Swch Service
H09FVE	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 48p 1G Fib Swch Service
H64B3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6300M 48p SR5 PoE SVC
HL8B3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300F 24 PoE Switch SVC
HL8K1E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300F 24 Switch SVC
HL7X4E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300F 48 PoE Switch SVC
HR6T6E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300F 48 Switch SVC
H08QZE	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 16p CL8 Swch Service
HR5J3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 24 PoE Switch SVC
HL6D6E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 24 SR PoE Switch SVC
HL7T5E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 24 Switch SVC
HR4H5E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 24SFP Switch SVC
H63N3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 24SR PoE SVC
H08VYE	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 24p 1G Fib Swch Service
H64Q5E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 24p SFP+ LRM SVC
H08ZXE	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 32p CL8 Swch Service
HR5E4E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 48 PoE Switch SVC
HL6H5E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 48 SR PoE Switch SVC
HR5S8E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 48 Switch SVC
H59F3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 48 Switch SVC
H14KYE	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 48SR10 Swch Service
H14PTE	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 48SR10 TAA Swch Service
H09FWE	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 48p 1G Fib Swch Service
H64B4E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6300M 48p SR5 PoE SVC
H08WFE	HPE Aruba Networking Foundational Care 5Y 4HR OS Technical Support V T2 6300M 24p 1GFib Swch Service
H09GCE	HPE Aruba Networking Foundational Care 5Y 4HR OS Technical Support V T2 6300M 48p 1GFib Swch Service
H08RGE	HPE Aruba Networking Foundational Care 5Y 4HR OS Technical Support Vol T2 6300M 16p CL8 Swch Service

H09BDE	HPE Aruba Networking Foundational Care 5Y 4HR OS Technical Support Vol T2 6300M 32p CL8 Swch Service
HR6H1E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300F 24 PoE Switch SVC
HR7A1E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300F 24 Switch SVC
HR5Y6E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300F 48 PoE Switch SVC
HR6R6E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300F 48 Switch SVC
H08NZE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 16p CL8 Swch Service
HL6T9E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 24 PoE Switch SVC
HR4K4E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 24 SR PoE Switch SVC
HL7L9E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 24 Switch SVC
HL5T1E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 24SFP Switch SVC
H63F7E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 24SR PoE SVC
H08SYE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 24p 1G Fib Swch Service
H64H9E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 24p SFP+ LRM SVC
H08XXE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 32p CL8 Swch Service
HR5C4E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 48 PoE Switch SVC
HR4T9E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 48 SR PoE Switch SVC
HL7C4E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 48 Switch SVC
H58U9E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 48 Switch SVC
H14HYE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 48SR10 Swch Service
H14MTE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 48SR10 TAA Swch Service
H09CWE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 48p 1G Fib Swch Service
H63U8E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6300M 48p SR5 PoE SVC
HR6H2E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300F 24 PoE Switch SVC
HR7A2E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300F 24 Switch SVC
HR5Y7E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300F 48 PoE Switch SVC
HR6R7E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300F 48 Switch SVC
H08PBE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300M 16p CL8 Swch Service
HL6U0E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300M 24 PoE Switch SVC
HR4K5E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300M 24 SR PoE Switch SVC
HL7M0E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300M 24 Switch SVC
HL5T2E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300M 24SFP Switch SVC
H08SZE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300M 24p 1G Fib Swch Service
H08XYE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300M 32p CL8 Swch Service
HR5C5E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300M 48 PoE Switch SVC
HR4U0E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300M 48 SR PoE Switch SVC

HL7C5E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300M 48 Switch SVC
H58V0E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300M 48 Switch SVC
H14HZE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300M 48SR10 Swch Service
H14MVE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300M 48SR10 TAA Swch Service
H09CXE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6300M 48p 1G Fib Swch Service
H08NYE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite HW Only 6300M 16p CL8 Swch Service
H08SXE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite HW Only 6300M 24p 1G Fib Swch Service
H08XWE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite HW Only 6300M 32p CL8 Swch Service
H09CVE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite HW Only 6300M 48p 1G Fib Swch Service
HR6H0E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300F 24 PoE Switch SVC
HR7A0E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300F 24 Switch SVC
HR5Y5E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300F 48 PoE Switch SVC
HR6R5E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300F 48 Switch SVC
HL6T8E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300M 24 PoE Switch SVC
HR4K3E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300M 24 SR PoE Switch SVC
HL7L8E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300M 24 Switch SVC
HL5T0E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300M 24SFP Switch SVC
H63F6E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300M 24SR PoE SVC
H64H8E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300M 24p SFP+ LRM SVC
HR5C3E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300M 48 PoE Switch SVC
HR4T8E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300M 48 SR PoE Switch SVC
H58U8E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300M 48 Switch SVC
HL7C3E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300M 48 Switch SVC
H63U7E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6300M 48p SR5 PoE SVC
H08PCE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Technical Support 6300M 16p CL8 Swch Service
H08TBE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Technical Support 6300M 24p 1G Fib Swch Service
H08XZE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Technical Support 6300M 32p CL8 Swch Service
H09CYE	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Technical Support 6300M 48p 1G Fib Swch Service
H63F8E	HPE Aruba Networking Foundational Care 5Y 24x7 CDMR 6300M 24SR PoE SVC
H64J0E	HPE Aruba Networking Foundational Care 5Y 24x7 CDMR 6300M 24p SFP+ LRM SVC
H63U9E	HPE Aruba Networking Foundational Care 5Y 24x7 CDMR 6300M 48p SR5 PoE SVC
H01HGE	HPE Aruba Networking Foundational Care 5Y 24x7 Technical Support 6300L 24 SW SVC
H01PME	HPE Aruba Networking Foundational Care 5Y 24x7 Technical Support 6300L 48 SW SVC

H01LNE	HPE Aruba Networking Foundational Care 5Y 24x7 Technical Support Vol T 26300L 24 SW SVC
H01STE	HPE Aruba Networking Foundational Care 5Y 24x7 Technical Support Vol T 26300L 48 SW SVC
H01HFE	HPE Aruba Networking Foundational Care 5Y 24x7 with CDMR 6300L 24 SW SVC
H01PLE	HPE Aruba Networking Foundational Care 5Y 24x7 with CDMR 6300L 48 SW SVC
HR6H4E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6300F 24 PoE Switch SVC
HR7A4E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6300F 24 Switch SVC
HR5Y9E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6300F 48 PoE Switch SVC
HR6R9E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6300F 48 Switch SVC
HL6U2E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6300M 24 PoE Switch SVC
HR4K7E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6300M 24 SR PoE Switch SVC
HL7M2E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6300M 24 Switch SVC
HL5T4E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6300M 24SFP Switch SVC
HR5C7E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6300M 48 PoE Switch SVC
HR4U2E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6300M 48 SR PoE Switch SVC
HL7C7E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6300M 48 Switch SVC
H58V2E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6300M 48 Switch SVC
HR6H5E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6300F 24 PoE Switch SVC
HR7A5E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6300F 24 Switch SVC
HR5Z0E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6300F 48 PoE Switch SVC
HR6S0E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6300F 48 Switch SVC
HL6U3E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6300M 24 PoE Switch SVC
HR4K8E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6300M 24 SR PoE Switch SVC
HL7M3E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6300M 24 Switch SVC
HL5T5E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6300M 24SFP Switch SVC
HR5C8E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6300M 48 PoE Switch SVC
HR4U3E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6300M 48 SR PoE Switch SVC
HL7C8E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6300M 48 Switch SVC
H58V3E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6300M 48 Switch SVC
H01HHE	HPE Aruba Networking Foundational Care 5Y CTR 6300L 24 SW SVC
H01PNE	HPE Aruba Networking Foundational Care 5Y CTR 6300L 48 SW SVC
H08PDE	HPE Aruba Networking Foundational Care 5Y CTR 6300M 16p CL8 Swch Service
H63GOE	HPE Aruba Networking Foundational Care 5Y CTR 6300M 24SR PoE SVC
H08TCE	HPE Aruba Networking Foundational Care 5Y CTR 6300M 24p 1G Fib Swch Service
H64J2E	HPE Aruba Networking Foundational Care 5Y CTR 6300M 24p SFP+ LRM SVC
H08YBE	HPE Aruba Networking Foundational Care 5Y CTR 6300M 32p CL8 Swch Service
H14JCE	HPE Aruba Networking Foundational Care 5Y CTR 6300M 48SR10 Swch Service

H14MXE	HPE Aruba Networking Foundational Care 5Y CTR 6300M 48SR10 TAA Swch Service
H09CZE	HPE Aruba Networking Foundational Care 5Y CTR 6300M 48p 1G Fib Swch Service
H63V1E	HPE Aruba Networking Foundational Care 5Y CTR 6300M 48p SR5 PoE SVC
H08PFE	HPE Aruba Networking Foundational Care 5Y CTR CDMR 6300M 16p CL8 Swch Service
H63G1E	HPE Aruba Networking Foundational Care 5Y CTR CDMR 6300M 24SR PoE SVC
H08TDE	HPE Aruba Networking Foundational Care 5Y CTR CDMR 6300M 24p 1G Fib Swch Service
H64J3E	HPE Aruba Networking Foundational Care 5Y CTR CDMR 6300M 24p SFP+ LRM SVC
H08YCE	HPE Aruba Networking Foundational Care 5Y CTR CDMR 6300M 32p CL8 Swch Service
H14JDE	HPE Aruba Networking Foundational Care 5Y CTR CDMR 6300M 48SR10 Swch Service
H14MYE	HPE Aruba Networking Foundational Care 5Y CTR CDMR 6300M 48SR10 TAA Swch Service
H09DBE	HPE Aruba Networking Foundational Care 5Y CTR CDMR 6300M 48p 1G Fib Swch Service
H63V2E	HPE Aruba Networking Foundational Care 5Y CTR CDMR 6300M 48p SR5 PoE SVC
H01HJE	HPE Aruba Networking Foundational Care 5Y CTR with CDMR 6300L 24 SW SVC
H01PPE	HPE Aruba Networking Foundational Care 5Y CTR with CDMR 6300L 48 SW SVC
H01GXE	HPE Aruba Networking Foundational Care 5Y NBD 6300L 24 SW SVC
H01PDE	HPE Aruba Networking Foundational Care 5Y NBD 6300L 48 SW SVC
H08NVE	HPE Aruba Networking Foundational Care 5Y NBD 6300M 16p CL8 Swch Service
H63F2E	HPE Aruba Networking Foundational Care 5Y NBD 6300M 24SR PoE SVC
H08STE	HPE Aruba Networking Foundational Care 5Y NBD 6300M 24p 1G Fib Swch Service
H64H4E	HPE Aruba Networking Foundational Care 5Y NBD 6300M 24p SFP+ LRM SVC
H08XSE	HPE Aruba Networking Foundational Care 5Y NBD 6300M 32p CL8 Swch Service
H09CRE	HPE Aruba Networking Foundational Care 5Y NBD 6300M 48p 1G Fib Swch Service
H63U3E	HPE Aruba Networking Foundational Care 5Y NBD 6300M 48p SR5 PoE SVC
H08NWE	HPE Aruba Networking Foundational Care 5Y NBD CDMR 6300M 16p CL8 Swch Service
H63F3E	HPE Aruba Networking Foundational Care 5Y NBD CDMR 6300M 24SR PoE SVC
H08SVE	HPE Aruba Networking Foundational Care 5Y NBD CDMR 6300M 24p 1G Fib Swch Service
H64H5E	HPE Aruba Networking Foundational Care 5Y NBD CDMR 6300M 24p SFP+ LRM SVC
H08XTE	HPE Aruba Networking Foundational Care 5Y NBD CDMR 6300M 32p CL8 Swch Service
H09CSE	HPE Aruba Networking Foundational Care 5Y NBD CDMR 6300M 48p 1G Fib Swch Service
H63U4E	HPE Aruba Networking Foundational Care 5Y NBD CDMR 6300M 48p SR5 PoE SVC
HR6G4E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300F 24 PoE Switch SVC
HR6Z4E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300F 24 Switch SVC
HR5X9E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300F 48 PoE Switch SVC
HR6Q9E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300F 48 Switch SVC
H01GVE	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300L 24 SW SVC
H01PBE	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300L 48 SW SVC

H08NSE	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 16p CL8 Swch Service
HL6T2E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 24 PoE Switch SVC
HL6A9E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 24 SR PoE Switch SVC
HL7L2E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 24 Switch SVC
HL5S4E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 24SFP Switch SVC
H63F0E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 24SR PoE SVC
H08SRE	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 24p 1G Fib Swch Service
H64H2E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 24p SFP+ LRM SVC
H08XQE	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 32p CL8 Swch Service
HR5B7E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 48 PoE Switch SVC
HR4T2E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 48 SR PoE Switch SVC
HL7B7E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 48 Switch SVC
H58U2E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 48 Switch SVC
H14HSE	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 48SR10 Swch Service
H14MME	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 48SR10 TAA Swch Service
H09CNE	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 48p 1G Fib Swch Service
H63U1E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6300M 48p SR5 PoE SVC
H08NRE	HPE Aruba Networking Foundational Care 5Y NBD Exch HW Only 6300M 16p CL8 Swch Service
H08SQE	HPE Aruba Networking Foundational Care 5Y NBD Exch HW Only 6300M 24p 1G Fib Swch Service
H08XNE	HPE Aruba Networking Foundational Care 5Y NBD Exch HW Only 6300M 32p CL8 Swch Service
H14HRE	HPE Aruba Networking Foundational Care 5Y NBD Exch HW Only 6300M 48SR10 Swch Service
H14MLE	HPE Aruba Networking Foundational Care 5Y NBD Exch HW Only 6300M 48SR10 TAA Swch Service
H09CME	HPE Aruba Networking Foundational Care 5Y NBD Exch HW Only 6300M 48p 1G Fib Swch Service
HR6G3E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300F 24 PoE Switch SVC
HR6Z3E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300F 24 Switch SVC
HR5X8E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300F 48 PoE Switch SVC
HR6Q8E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300F 48 Switch SVC
H01GTE	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300L 24 SW SVC
H01NZE	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300L 48 SW SVC
HL6T1E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300M 24 PoE Switch SVC
HL6A8E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300M 24 SR PoE Switch SVC
HL7L1E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300M 24 Switch SVC
HL5S3E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300M 24SFP Switch SVC
H63E9E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300M 24SR PoE SVC
H64H1E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300M 24p SFP+ LRM SVC
HR5B6E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300M 48 PoE Switch SVC

HR4T1E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300M 48 SR PoE Switch SVC
H58U1E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300M 48 Switch SVC
HL7B6E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300M 48 Switch SVC
H63U0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6300M 48p SR5 PoE SVC
HL8A8E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300F 24 PoE Switch SVC
HL8J6E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300F 24 Switch SVC
HL7W9E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300F 48 PoE Switch SVC
HR6T1E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300F 48 Switch SVC
H01LBE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300L 24 SW SVC
H01SHE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300L 48 SW SVC
H08QTE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 16p CL8 Swch Service
HL7A0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 24 PoE Switch SVC
HL6D1E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 24 SR PoE Switch SVC
HL7T0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 24 Switch SVC
HR4H0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 24SFP Switch SVC
H63M8E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 24SR PoE SVC
H08VSE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 24p 1G Fib Swch Service
H64Q0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 24p SFP+ LRM SVC
H08ZRE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 32p CL8 Swch Service
HR5D9E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 48 PoE Switch SVC
HL6H0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 48 SR PoE Switch SVC
HR5S3E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 48 Switch SVC
H59E8E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 48 Switch SVC
H14KSE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 48SR10 Swch Service
H14PME	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 48SR10 TAA Swch Service
H09FQE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 48p 1G Fib Swch Service
H64A9E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6300M 48p SR5 PoE SVC
HL8A9E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300F 24 PoE Switch SVC
HL8J7E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300F 24 Switch SVC
HL7X0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300F 48 PoE Switch SVC
HR6T2E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300F 48 Switch SVC
H01LCE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300L 24 SW SVC
H01SJE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300L 48 SW SVC
H08QVE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 16p CL8 Swch Service
HL7A1E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 24 PoE Switch SVC
HL6D2E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 24 SR PoE Switch SVC

HL7T1E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 24 Switch SVC
HR4H1E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 24SFP Switch SVC
H63M9E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 24SR PoE SVC
H08VTE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 24p 1G Fib Swch Service
H64Q1E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 24p SFP+ LRM SVC
H08ZSE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 32p CL8 Swch Service
HR5E0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 48 PoE Switch SVC
HL6H1E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 48 SR PoE Switch SVC
HR5S4E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 48 Switch SVC
H59E9E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 48 Switch SVC
H14KTE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 48SR10 Swch Service
H14PNE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 48SR10 TAA Swch Service
H09FRE	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 48p 1G Fib Swch Service
H64B0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6300M 48p SR5 PoE SVC
HR6G6E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6300F 24 PoE Switch SVC
HR6Z6E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6300F 24 Switch SVC
HR5Y1E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6300F 48 PoE Switch SVC
HR6R1E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6300F 48 Switch SVC
HL6T4E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6300M 24 PoE Switch SVC
HL6B1E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6300M 24 SR PoE Switch SVC
HL7L4E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6300M 24 Switch SVC
HL5S6E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6300M 24SFP Switch SVC
HR5B9E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6300M 48 PoE Switch SVC
HR4T4E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6300M 48 SR PoE Switch SVC
HL7B9E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6300M 48 Switch SVC
H58U4E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6300M 48 Switch SVC
H14HVE	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6300M 48SR10 Swch Service
H14MQE	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6300M 48SR10 TAA Swch Service
HR6G7E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6300F 24 PoE Switch SVC
HR6Z7E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6300F 24 Switch SVC
HR5Y2E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6300F 48 PoE Switch SVC
HR6R2E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6300F 48 Switch SVC
HL6T5E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6300M 24 PoE Switch SVC
HL6B2E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6300M 24 SR PoE Switch SVC
HL7L5E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6300M 24 Switch SVC
HL5S7E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6300M 24SFP Switch SVC

HR5C0E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6300M 48 PoE Switch SVC
HR4T5E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6300M 48 SR PoE Switch SVC
HL7C0E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6300M 48 Switch SVC
H58U5E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6300M 48 Switch SVC
H14HWE	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6300M 48SR10 Swch Service
H14MRE	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6300M 48SR10 TAA Swch Service
H01GYE	HPE Aruba Networking Foundational Care 5Y NBD with CDMR 6300L 24 SW SVC
H01PFE	HPE Aruba Networking Foundational Care 5Y NBD with CDMR 6300L 48 SW SVC
H14JBE	HPE Aruba Networking Foundational Care 5Y SW + Technical Support 6300M 48SR10 Swch Service
H14MWE	HPE Aruba Networking Foundational Care 5Y SW + Technical Support 6300M 48SR10 TAA Swch Service
H14LFE	HPE Aruba Networking Foundational Care 5Y SW + Technical Support Vol T2 6300M 48SR10 Swch Service
H14PZE	HPE Aruba Networking Foundational Care 5Y SW +Technical Support Vol T2 6300M 48SR10 TAA Swch Service
H58V5PE	HPE Aruba Networking RNWL Foundational Care 1Y 4HR Exch 6300M 48 Switch SVC
H58Y3PE	HPE Aruba Networking RNWL Foundational Care 1Y 4HR Exch Vol T1 6300M 48 Switch SVC
H58Y4PE	HPE Aruba Networking RNWL Foundational Care 1Y 4HR Exch Vol T2 6300M 48 Switch SVC
H58W1PE	HPE Aruba Networking RNWL Foundational Care 1Y 4HR Onsite 6300M 48 Switch SVC
H58W2PE	HPE Aruba Networking RNWL Foundational Care 1Y 4HR Onsite CDMR 6300M 48 Switch SVC
H58WOPE	HPE Aruba Networking RNWL Foundational Care 1Y 4HR Onsite Hardware Only 6300M 48 Switch SVC
H58W3PE	HPE Aruba Networking RNWL Foundational Care 1Y CTR 6-Hour 6300M 48 Switch SVC
H58W4PE	HPE Aruba Networking RNWL Foundational Care 1Y CTR 6-Hour CDMR 6300M 48 Switch SVC
H58V4PE	HPE Aruba Networking RNWL Foundational Care 1Y NBD Exch 6300M 48 Switch SVC
H58X9PE	HPE Aruba Networking RNWL Foundational Care 1Y NBD Exch Vol T1 6300M 48 Switch SVC
H58YOPE	HPE Aruba Networking RNWL Foundational Care 1Y NBD Exch Vol T2 6300M 48 Switch SVC
H58V6PE	HPE Aruba Networking RNWL Foundational Care 1Y NBD Onsite 6300M 48 Switch SVC
H58V7PE	HPE Aruba Networking RNWL Foundational Care 1Y NBD Onsite CDMR 6300M 48 Switch SVC

HPE Aruba Networking Services

HPE Aruba Networking services simplify and accelerate the network technology lifecycle, enabling your network to scale with better predictability and cost-effectiveness. Whether you operate your own network and need to improve your IT efficiencies, or you want to offload some of the burden, we have the services you need to reach your goals.

Learn more about what HPE Services - Aruba Networking has to offer at: hpe.com/edge/services

Support Services

Our support portfolio provides the essential support elements as well as proactive and preventive features to help you improve your team's productivity and get the most from your network. Our support customers benefit from faster issue resolution, simplified operations and efficiencies, and reduced network issues.

Professional Services

With deep intellectual capital and purpose-built tools, our team delivers a range of standard and custom professional services designed to accelerate your value from HPE Aruba Networking technology.

Project based services include:

- Planning, audit, and assessment
- Architecture review and design
- Deployment, migration, and knowledge transfer

Annual subscription services include:

- Network optimization
- Intelligent Operations
- Customer Experience Management

Our [Education Services](#) allow your team to come up to speed quickly.

GreenLake for Networking

Deliver innovative business outcomes by leveraging new ways to consume, deploy and [manage networks](#).

For additional technical information,
available models and options, please
reference the QuickSpecs

Visit [HPE.com](https://www.hpe.com)

Chat now

© Copyright 2026 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

Parts and Materials: HPE will provide HPE-supported replacement parts and materials required to maintain the covered hardware.

Parts and components that have reached their maximum supported lifetime and/or the maximum usage limitations as set forth in the manufacturer's operating manual, product quick-specs, or the technical product data sheet will not be provided, repaired, or replaced as part of these services.

Arm and Arm Cortex are registered trademarks of Arm Limited. Microsoft is either a registered trademark or a trademark of Microsoft Corporation in the United States and/or other countries. SAP and SAP HANA are trademarks or registered trademark of SAP SE (or an SAP affiliate company) in Germany and other countries. VMware is a trademark or registered trademark of VMware, LLC or its affiliates in the United States and other countries. All third-party marks are property of their respective owners.

Image may differ from the actual product.

PSN1012138130USEN, August, 2026.

HEWLETT PACKARD ENTERPRISE

[hpe.com](https://www.hpe.com)

